

STATE OF CONNECTICUT

CONNECTICUT SITING COUNCIL

Ten Franklin Square, New Britain, CT 06051 Phone: (860) 827-2935 Fax: (860) 827-2950 E-Mail: siting.council@po.state.ct.us www.ct.gov/csc

December 19, 2005

New Cingular Wireless PCS, LLC c/o David Malko 36 Quarry Road Chester, VT 05143

RE: EM-CING-138-135-034-015-051130 - New Cingular Wireless PCS, LLC notice of intent to modify existing telecommunications facilities located at 623 Honeyspot Road, Stratford; 555 Main Street, Stamford; 39 West Street, Danbury; Moses Mountain, Danbury; and 430 John Street, Bridgeport, Connecticut.

Dear Mr. Malko:

At a public meeting held on December 14, 2005, the Connecticut Siting Council (Council) acknowledged your notice to modify all of these existing telecommunications facilities except the Moses Mountain, Danbury site, pursuant to Section 16-50j-73 of the Regulations of Connecticut State Agencies, with the following conditions:

- 1. The Stratford tower is modified per Appendix B of the structural analysis report dated October 3, 2005 and signed Oscar Pedraza, P.E. prior to the antenna swap and that a letter signed by a Professional Engineer is submitted to the Council to certify that the modifications have been properly completed.
- 2. The Stamford site is modified as specified on the structural analysis letter sealed by Demirtas Bayar, P.E. and that a letter signed by a Professional Engineer is submitted to the Council to certify that the modifications have been properly completed.

The Council tabled the Moses Mountain proposal pending the receipt of additional information on the RF power density. This item will be presented at a future Council meeting.

The proposed modifications are to be implemented as specified here and in your notice dated November 30, 2005, including the placement of all necessary equipment and shelters within the tower compounds. The modifications are in compliance with the exception criteria in Section 16-50j-72 (b) of the Regulations of Connecticut State Agencies as changes to existing facility sites that would not increase tower heights, extend the boundaries of the tower sites, increase noise levels at the tower site boundaries by six decibels, and increase the total radio frequencies electromagnetic radiation power densities measured at the tower site boundaries to or above the standard adopted by the State Department of Environmental Protection pursuant to General Statutes § 22a-162. These facilities have also been carefully modeled to ensure that radio frequency emissions are conservatively below State and federal standards applicable to the frequencies now used on these towers.

This decision is under the exclusive jurisdiction of the Council. Please be advised that the validity of this action shall expire one year from the date of this letter. Any additional change to any of these facilities will require explicit notice to this agency pursuant to Regulations of Connecticut State Agencies Section 16-50j-73. Such notice shall include all relevant information regarding the proposed change with cumulative worst-case modeling of radio frequency exposure at the closest point of uncontrolled access to the tower base, consistent with Federal Communications Commission, Office of Engineering and Technology, Bulletin 65. Any deviation from this format may result in the Council implementing enforcement proceedings pursuant to General Statutes § 16-50u including, without limitation, imposition of expenses resulting from such failure and of civil penalties in an amount not less than one thousand dollars per day for each day of construction or operation in material violation.



Thank you for your attention and cooperation.

Very truly yours,

Pamela B. Katz, P.E.

Chairman

PBK/laf

c: The Honorable John Fabrizi, Mayor, City of Bridgeport Melanie J. Howlett, Assistant City Attorney, City of Bridgeport The Honorable Mark D. Boughton, Mayor, City of Danbury Dennis Elpern, City Planner, City of Danbury The Honorable Dannel P. Malloy, Mayor, City of Stamford Robert Stein, Planning and Zoning Director, City of Stamford The Honorable James R. Miron, Town Manager, Town of Stratford Gary Lorentson, Planning & Zoning Administrator, Town of Stratford Christopher B. Fisher, Esq., Cuddy & Feder LLP Kenneth C. Baldwin, Esq., Robinson & Cole LLP Thomas J. Regan, Esq., Brown Rudnick Berlack Israels LLP Thomas F. Flynn III, Nextel Communications Inc. Christine Farrell, T-Mobile FAX

DAVID MARTIN

FROM DAVE MALKU

DAR 12/13/05

Sist: Power Densty detail for Exempt mod filmes

FART 860-827-2950

(3 pages inc cover)

11/30/05 and 12/12/05

Attached is the PD detail for my last 2 filings (11/30/05 4 12/1405).

Call with any questions, Dave. Hone/office: 802-875-4514 Cell : 860-301-6378

Cingular	Cingular Sitel	Carrier	#Channels	ERP/Ch	Ant Ht	Density (m)	MHZ	Ø	%MPE	Cing Total
2176		CINGULAR GSM	7	286	148	0.0340	880	0.5867	5.80%	
2176		CINGULAR GSM	2	427	148	0.0140	1930	1.0000	1.40%	
2176	Bridgeport - 430 John Street	SNET	17	40	148	0.0112	850	0.5667	1.97%	9.17%
2124		CINGULAR GSM	4	286	69	0.0894	880	0.5867	15.24%	
2124		CINGULAR GSM	-	427	69	0.0322	1930	1.0000	3.22%	
2124	Danbury - 39 West Street	SNET/Cingular	16	40	2	0.0470	880	0.5867	8.01%	26.47%
2133	Danbury - Moses Mountain	SNET - Cellular	12	100	63.79	0.1060	850	0.5667	18.71%	
2133		CINGULAR GSM	7	296	65	0.0504	880	0.5867	8.59%	
2133		CINGULAR GSM	7	427	65	0.0727	1930	1.0000	7.27%	34.57%
2118	Stamford - 555 Main Street	Cingular/SNET	23	40	226	0.0065	880	0.5867	1.10%	
2118		Cingular GSM	œ	296	235	0.0154	880	0.5867	2.63%	
2118		Cingular GSM	7	427	235	0.0056	1930	1.0000	0.56%	4.29%
2112		Cingular GSM	ω	296	92	0.1008	880	0.5867	17.15%	
2112		Cingular GSM	7	427	92	0.0363	1930	1.0000	3.63%	
2112	Strafford - 623-627 Honeyspot Road	Cingular	14	40	06	0.0249	880	0.5867	4.24%	25.01%

November 30, 2005 ALING


Cingular Sitell Site	r Sitell <u>Site</u> #Channels ERP/Ch Ant H	Carrier	#Channels	ERP/Ch	Ant Ht	Density (m)	MH2	ď	MUM W	Cian Total
2094		CINGULARGSM		206	100	0.000		1001	1 1000	CILIS I CILIS
			•	200	3	0.0460	200	0.0867	0,797	
2084	Westport - Sunny Lane	CINGULAR GSM	~~	427	100	0.0154	1030	0000	4 5.40/	
7000	Machany Change and	+ 0 + <	. (2			2000	0/10	
1	restport : Sumiy Laile	Alai	>	250	90	0.000	1945	1.0000	%00.0	8.79%
2153	Westport - 515 Boston Post Road	SNET/Cinquiar	12	40	120	0.0420	Can	0 5067	2 0.40/	
		3	ļ	•		2	2	2007.0	6,40.7	
	westport - 515 Boston Post Road	CINGULAR GSM	m	298	120	0.0222	880	0.5887	3 78%	
24.63	TATIONAL TATION OF THE PARTY OF				1					
- 1	Westport - 515 Boston Post Road	CINGULAR GSM	-	427	120	0.0107	1930	1.0000	1.07%	6.89%
CT0093	Bridgeport - 1330 Chopsey Hill Road/1	000 AT&T TOMA	c	116.2	186	0000	1015	1 0000	/000	
S COULT			•		3		7	2000:	0.00	
560015	Bridgeport - 1330 Chopsey HIII Road/	000 AT&T GSM	ĸ	275	165	0.0182	1945	1 0000	1 87%	
10001							,		1,40.	
2800		A1&1 GSM	_	296	165	0.0274	880	0.5867	4 66%	
70007	AND THE PROPERTY OF THE PROPER	1110000	•	•						
2000	oringeport - 1550 Chopsey Hill Road?	ODE SINE I	20	100	28	0.0288	880	0.5867	4 91%	11.30%

December 12, 2005 Guma



EM-CING-138-135-034-015-051130

November 30, 2005



Mr. S. Derek Phelps Executive Director Connecticut Siting Council 10 Franklin Square New Britain, CT 06051

Re: Notice of Exempt Modifications to Various Facilities in the Towns of Stratford, Stamford, Danbury and Bridgeport, Connecticut

Dear Mr. Phelps:

As part of its merger and integration efforts, New Cingular Wireless PCS, LLC ("Cingular" or "the Company") intends to modify instrumentation and/or antenna configurations at five existing facilities located in the Towns of Stratford, Stamford, Danbury and Bridgeport, Connecticut. Please accept this letter and attachments as notification, pursuant to R.C.S.A. § 16-50j-73, of construction that constitutes exempt modifications pursuant to R.C.S.A. § 16-50j-72(b)(2). In accordance with R.C.S.A. § 16-50j-73, a copy of this letter and attachments is being sent to the chief elected official of each of the municipalities in which an affected cell is located.

The five sites which are the subject of this filing have been grouped based on their location and proximity and are discussed in more detail below. Additional exempt modification notifications will follow in the near future and will cover similarly grouped facilities within the balance of Fairfield County.

General

The current project involves changes at most of Cingular's cell sites in Fairfield County including over 40 sites under Council jurisdiction. The modifications will allow Cingular to operate its wireless communications services in the 1900 MHz frequency band in addition to its 850 MHz operations. At a typical site, this will be accomplished through the removal of nine (9) existing 850 MHz only antennas and their replacement with six (6) 850/1900 MHz dual-band antennas. Since each of the new, dual-band antennas is fed by two transmission lines, the typical number of such transmission lines at each site will increase from nine to a total of 12. In addition, tower mounted amplifiers, diplexers and small miscellaneous electronics will also be installed on the antenna platforms. The new antennas, transmission lines and tower mounted equipment have

Mr. S. Derek Phelps November 30, 2005 Page 2

been properly reflected in the structural analyses performed for the towers and attached to this filing. A more detailed analysis of each of the five sites follows.

Site 1

Site 1 is located at 623 Honeyspot Road, Stratford, CT and is owned by Becker, LLC (Cingular Site #2112). On the property are a 100-foot monopole tower, a large building, and several equipment shelters. In addition to Cingular, the tower currently supports antennas of wireless carriers AT&T Wireless, Nextel, Verizon and Sprint as well as Com-tronics and Metricom.

Cingular proposes to remove their nine (9) existing single-band antennas and install six (6) Powerwave Model 7770.00 dual-band directional antennas. The new antennas are 55" in height and will be mounted on the same platform as the existing antennas with a center of radiation of 92' above ground level (AGL). Six (6) tower mounted amplifiers and six (6) diplexers along with miscellaneous electronics to provide remote downtilting capabilities will also be installed on the existing antenna platform. Technical specification sheets for the antennas, amplifiers and diplexers are included the General Information section of the attachments to this notice. Additional radio equipment will be located within the Company's existing 12' x 16' equipment shelter. Since each new antenna requires two feeds from the radio equipment, new transmission lines will be added to the tower bringing the total number of lines to 12. An analysis has been performed for the tower taking into account the new antennas, transmission lines and other equipment and is included in the site specific section of the attachments. Site plans, elevations and photographs of the site are also included.

Based on the most recent filing for this site, the "worst-case" predicted RF power density for a point at the base of the tower, excluding the operations of Cingular and AT&T Wireless, is calculated to be approximately 45.58% of the applicable standard for uncontrolled environments as calculated for a mixed frequency site. A similar "worst-case" calculation for a point at the base of the tower indicates that when fully implemented, New Cingular's dual-band operations would contribute approximately 25.02% of the standard. The calculated "worst-case" power density for the combined operations at the site would therefore be approximately 70.60% of the applicable standard for uncontrolled environments as calculated for a mixed frequency site.

Site 2

Site 2 is located at 555 Main Street, Stamford, CT and is owned by SBC (Cingular Site #2118). On the property is a 125-foot lattice tower located on the roof of a 105-foot

Mr. S. Derek Phelps November 30, 2005 Page 3

building. In addition to Cingular, the tower currently supports antennas of wireless carrier T-Mobile as Well as WinStar, PageNet and Broadcast Video.

Cingular proposes to remove their nine (9) existing single-band antennas and install six (6) Powerwave Model 7770.00 dual-band directional antennas. The new antennas are 55" in height and will be mounted on the same platform as the existing antennas with a center of radiation of 235' above ground level (AGL). Six (6) tower mounted amplifiers and six (6) diplexers along with miscellaneous electronics to provide remote downtilting capabilities will also be installed on the existing antenna platform. Technical specification sheets for the antennas, amplifiers and diplexers are included the General Information section of the attachments to this notice. Additional radio equipment will be located within the Company's existing equipment room within the building. Since each new antenna requires two feeds from the radio equipment, new transmission lines will be added to the tower bringing the total number of lines to 12. An analysis has been performed for the tower taking into account the new antennas, transmission lines and other equipment and is included in the site specific section of the attachments. Site plans, elevations and photographs of the site are also included.

Based on the most recent filing for this site, the "worst-case" predicted RF power density for a point at the base of the building, excluding the operations of Cingular, is calculated to be approximately 9.45% of the applicable standard for uncontrolled environments as calculated for a mixed frequency site. A similar "worst-case" calculation for a point at the base of the building indicates that when fully implemented, New Cingular's dual-band operations would contribute approximately 4.29% of the standard. The calculated "worst-case" power density for the combined operations at the site would therefore be approximately 13.74% of the applicable standard for uncontrolled environments as calculated for a mixed frequency site.

Site 3

Site 3 is located at 39 West Street, Danbury, CT and is owned by SBC (Cingular Site #2124). On the property is a 39-foot lattice tower and support pipe located on the roof of a 33-foot building. No other carriers are located at the site.

Cingular proposes to remove their three (3) existing single-band antennas and install six (3) Powerwave Model 7770.00 dual-band directional antennas. The new antennas are 55" in height and will be mounted at the same location behind a stealth antenna shroud as the existing antennas with a center of radiation of 69' above ground level (AGL). Six (6) tower mounted amplifiers along with miscellaneous electronics to provide remote downtilting capabilities will also be installed on the tower. Technical specification sheets for the antennas, amplifiers and diplexers are included the General Information section of the attachments to this notice. Additional radio equipment will be located within the Company's existing 21' x 32' equipment room within the building. Since each new antenna requires two feeds from the radio equipment, new transmission

Mr. S. Derek Phelps November 30, 2005 Page 4

lines will be added to the tower bringing the total number of lines to 6. A structural analysis has been performed for the tower taking into account the new antennas, transmission lines and other equipment and is included in the site specific section of the attachments. Site plans, elevations and photographs of the site are also included.

The "worst-case" predicted RF power density for a point at the base of the building, when New Cingular's dual-band operations is fully implemented, is calculated to be approximately 26.47% of the applicable standard for uncontrolled environments as calculated for a mixed frequency site.

Site 4

Site 4 is located on Moses Mountain, Danbury, CT and is owned by RCC Consultants (Cingular Site #2133). On the property are a 65-foot lattice tower and several equipment shelters. In addition to Cingular, the tower currently supports antennas of wireless carrier Verizon.

Cingular proposes to remove their twelve (12) existing single-band antennas and install six (6) Powerwave Model 7770.00 dual-band directional antennas. The new antennas are 55" in height and will be mounted on the same platform as the existing antennas with a center of radiation of 65' above ground level (AGL). Six (6) tower mounted amplifiers and six (6) diplexers along with miscellaneous electronics to provide remote downtilting capabilities will also be installed on the existing antenna platform. Technical specification sheets for the antennas, amplifiers and diplexers are included the General Information section of the attachments to this notice. Additional radio equipment will be located within the Company's existing 12' x 29' equipment room. Since each new antenna requires two feeds from the radio equipment, new transmission lines will be added to the tower bringing the total number of lines to 12. A structural analysis has been performed for the tower taking into account the new antennas, transmission lines and other equipment and is included in the site specific section of the attachments. Site plans, elevations and photographs of the site are also included.

The "worst-case" predicted RF power density for a point at the base of the tower, excluding the operations of Cingular, is calculated to be approximately 28.8% of the applicable standard for uncontrolled environments as calculated for a mixed frequency site. A similar "worst-case" calculation for a point at the base of the tower indicates that when fully implemented, New Cingular's dual-band operations would contribute approximately 34.57% of the standard. The calculated "worst-case" power density for the combined operations at the site would therefore be approximately 63.37% of the applicable standard for uncontrolled environments as calculated for a mixed frequency site.

Site 5

Site 5 is located at 430 John Street, Bridgeport, CT and is owned by RCC Consultants (Cingular Site #2176). On the property is an approximate 145-foot building with a roof-mounted lattice tower. The antennas associated with this modification are located on the parapet wall of the building and not on the tower. No other carriers are located at the site.

Cingular proposes to remove their nine (9) existing single-band antennas and install six (6) Powerwave Model 7770.00 dual-band directional antennas. The new antennas are 55" in height and will be mounted on the same mounting pipes as the existing antennas with a center of radiation of 148' above ground level (AGL). Six (6) tower mounted amplifiers along with miscellaneous electronics to provide remote downtilting capabilities will also be installed on the roof. Technical specification sheets for the antennas and amplifiers are included the General Information section of the attachments to this notice. Additional radio equipment will be located within the Company's existing 16' x 51' equipment room in the building. Since each new antenna requires two feeds from the radio equipment, new transmission lines will be added to the installation bringing the total number of lines to 6. An analysis has been performed for the antenna mounts taking into account the new antennas, transmission lines and other equipment and is included in the site specific section of the attachments. Site plans, elevations and photographs of the site are also included.

The "worst-case" predicted RF power density for a point at the base of the building, when New Cingular's dual-band operations is fully implemented, is calculated to be approximately 9.17% of the applicable standard for uncontrolled environments as calculated for a mixed frequency site.

Summary

The proposed changes to the facilities do not constitute modifications as defined in Connecticut General Statutes ('C.G.S.") § 16-50i(d) because the general physical characteristics of the facilities will not be significantly changed or altered. Rather, the planned modifications to the facilities fall squarely within those activities explicitly provided for in R.C.S.A. § 16-50j-72(b)(2).

1. The proposed modification will not increase the heights of the towers. In all cases, the number of antennas will be reduced and will result in a reduction in the towers'/buildings' profiles. The enclosed drawings confirm that the planned modifications will not increase the heights or the profiles of the towers/buildings. Based on the attached structural analyses, the facilities are capable of supporting the reconfigured loads discussed herein.

- 2. The installation of the proposed equipment, as reflected on the attached site plans, will not require an extension of the site boundaries.
- 3. The proposed modifications to the facility will not increase the noise levels at the existing facility by six decibels or more.
- 4. As discussed above, the operation of the reconfigured sites will not increase the total radio frequency (RF) power density to a level at or above the applicable standard.

For the foregoing reasons, New Cingular Wireless PCS, LLC respectfully submits that the proposed addition of antennas and equipment at the subject facilities constitute exempt modifications under R.C.S.A. § 16-50j-72(b)(2).

Sincerely,

David S. Malko, P.E. Consultant for New Cingular Wireless

Enclosures

cc: Honorable Joseph G. Crudo, Town Council Chairman, Stratford Honorable Dannel P. Malloy, Mayor, Stamford Honorable Mark D. Boughton, Mayor, Danbury Honorable John Fabrizi, Mayor, Bridgeport

General Information Attachments

- 1. Antenna Specifications
- 2. Tower Mounted Amplifier Specifications
- 3. Diplexer Specifications

Dual Broadband Antenna

90° 1.4 m MET Antenna

Part Number: 7770.00

Horizontal Beamwidth: 90° Gain: 13.5/16 dBi

Electrical Downtilt: Adjustable Connector Type: 7/16 female

The Powerwave dual band dual polarized broadband antenna has individual adjustable electrical downtilt per band (upgradeable to Remote Electrical Tilt (RET). Four connector ports allow separate tilts on each frequency band and ensure the use of diversity concepts. The phase shifter technology, based on a patented sliding dielectric, minimizes intermodulation distortion and maximizes efficiency. The slant +/- 45° dual polarization system provides the independent fading signals needed for achieving top-quality coverage via diversity concepts. The Powerwave Broadband antenna design is based on a patented stacked aperture-coupled patch technology, which provides high isolation performance and a wide VSWR bandwidth. The antennas have superior radiation patterns due to a unique reflector design which provides a very small variation of the –3dB horizontal beam width over the frequency band as well as a high front-to-back ratio.



Key Benefits

- · Excellent broad- and multi-band capabilities
- · Polarization purity makes good diversity gain
- Excellent pattern performance and high gain over frequency
- · High passive intermodulation performance
- · Light, slim and robust design



Preliminary





Dual Broadband Antenna

Electrical Specifications (Preliminary)

1				
١	Frequency band (MHz)	806-960		1710-2170
I	Gain, ± 0.5dB (dBi)	13.5		16.0
١	Polarization		Dual linear ±45°	
ı	Nominal Impedance (Ohm)		50	
١	VSWR	1.5:1		
	VSWR			1.5:1
	Isolation between inputs (dB)	30		
	Isolation between inputs (dB)			30
	Inter band isolation (dB)		40	
	Horizontal -3 dB beamwidth	85 ± 5°		85 ± 5°
	Tracking, Horizontal plane, ±60° (dB)	<2.0		
	Tracking, Horizontal plane, ±60° (dB)			<2.0
	Electrical downtilt range (adjustable)	0° to 10°		0° to 8°
	Vertical -3 dB beamwidth	14.3 ± 2.0°		6.6 ± 1°
	Sidelobe suppression, Vertical 1 st upper (dB)	>17,16,15		> 17, 16,15
		x=0, 5, 10° MET		x=0, 4, 8° MET
	Vertical beam squint	<0.8°		<0.5°
	First null-fill (dB)	<-25		<-25
	Front-to-back ratio (dB)	>25		>27
	Front-to-back ratio, total power (dB)	>20		>23
	IM3, 2Tx@43dBm (dBc)	<-153		
	IM3, 2Tx@43dBm (dBc)			<-153
	IM7, 2Tx@43dBm (dBc)			<-160
	Power Handling, Average per input (W)	400		250
	Power Handling, Average total (W)	800		500

All specifications are subject to change without notice.

Contact your Powerwave representative for complete performance data.

Mechanical Specifications

Connector Type 4 x 7/16 DIN female

Connector Position Bott

Dimensions, HxWxD 1408mm x 280mm x 125mm (55"x11"x5")

Weight Including Brackets

15.8 kg (35 lbs)

Wind Load, Frontal, 42m/s Cd=1

Survival Wind Speed (m/s)

Lightning Protection

Radome Material

15.8 kg (35 lbs)

435N (98 lbf)

70 (156mph)

DC grounded

Mounting Pre-mounted Standard Brackets

Packing Size 1550mm x 355mm x 255mm (61"x14"x10")

Light Gray

Corporate Headquarters

Radome Color

Powerwave Technologies, Inc. Tel: 714-4
1801 East St. Andrew Place
Santa Ana, CA 92705 USA

Tel: 714-4
Fax: 714-4
www.powe

Tel: 714-466-1000 Fax: 714-466-5800 www.powerwave.com Main European Office Antennvägen 6 SE-187 80 Täby Sweden Tel: +46 8 540 822 00 Fax: +46 8 540 823 40 Main Asia Pacific Office 23 F Tai Yau Building 181 Johnston Road Wanchai, Hong Kong Tel: +852 2512 6123 Fax: +852 2575 4860



CCopyright March 2005, Powerwave Technologies, Inc. All Rights reserved. Powerwave, Powerwave Technologies, The Power in Wireless and the Powerwave logo are registered trademarks of Powerwave Technologies, Inc.










Tower Mounted Amplifier

LGP21401 TMA-DD-1900 FB with 850 Bypass Tower Mounted Amplifier

Frequency: 1850-1990 MHz Band Gain: 12 dBd IMD Specification: <-118dBm Return Loss:18 dB or better

Powerwave's 21401 Series of tower mounted amplifiers are designed for full band coverage of the PCS-1900 band with an 800 MHz cellular band bypass. It has dual duplex capability so you can use one line for RX/TX and transmit through the TMA while amplifying RX on the same line. Deployed in a network it will increase capacity and coverage as well as extend the battery life time for the handsets. The 800 MHz cellular band passes through the TMA without amplification.







LGP21401 - Tower Mount Amplifier

Gain

12 dB

Uplink frequency

1850-1910 MHz

Downlink frequency

1930 - 1990 MHz

Return loss

18 dB or better

Noise figure

1.5 dB typical

Intermodulation@2x43dBm

<-118 dBm in receive band

carriers

Output 3rd order Intercept

>+22 dBm

Point (OIP3)

Rejection 1912 MHz (RX in

10 dB

80 dB

Filter)

Rejection in TX band Alarm functionality

Two levels, individually

supervised LNA branches

Power consumption

1.5 W per LNA @12 VDC

Supply voltage

9 - 15 V

Mechanical Specifications

RF connectors

7/16 DIN female(s)

Dimensions

14"x7"x2.7" (365x176x68mm)

Weight

17.5 lbs (<8kg)

Mounting kit

Mounting kit is included for pole and wall. Other types may be

available on request.

Corporate Headquarters

Main European Office

Powerwave Technologies, Inc. 1801 East St. Andrew Place Santa Ana, CA 92705 USA Tel: 714-466-1000 Fax: 714-466-5800

www.powerwave.com

Antennvägen 6 SE-187 80 Täby

Sweden +46 8 540 822 00 +46 8 540 824 85 FAX

THE POWER IN WIRELESS®

Powerwave Technologies, Inc. is an ISO8001 and TL8000 certified company, is a leading supplier of high performance RF infrastructure products for use in wireless communications networks. Powerwave products are utilized in both cellular and PCS base stations in both digital and analog networks. CCopyright February 2003, Powerwave Technologies, Inc. All Rights reserved. Powerwave Technologies are and the Powerwave logo are registered trademarks of Powerwave Technologies, Inc.

GLOBAL PARTNER

INTEGRATED SOLUTIONS

QUALITY AND RELIABILITY

824-896/1850-1990 MHz Diplexer

Diplexer for 824-896/1850-1990MHz with Configurable DC Transparency


Part Number: LGP13519 Frequency Range: 824-894/1850-

1990 MHz

| Return Loss: >20 dB

Insertion Loss: 0.2 dB / 0.3 dB

The Powerwave® Diplexer filter DCT is available both as single and double unit. Each diplexer has one port for 824-894 systems, one port for 1850-1990 GSM systems and a common port. It is designed for outdoor use and intended for co-location of base stations to enable sharing of feeder, TMA system and antenna. The unit can be used both at the BTS and for combining frequency bands to a common port and at the antenna end for splitting the frequency bands to separate antennas.



824-894/1850-1990 MHz Diplexer

Key Benefits:

- · Compact Design
- Inbuilt DC Transparency and Subcarrier Support
- · Excellent Power Handling
- Negligible Transmit Band Loss
- · Lightning Protected on All Ports











Electrical Specifications

800-900 Port Frequency Range, Full Band (MHz)

824-894 MHz Insertion Loss (dB) <0.2 dB Return Loss (dB) >20 dB >55 dB Rejection 1850-1990 MHz Rejection 2110-2170 MHz >55 dB Average Power Handling >500 W Peak Power 10 kW IM, 2Tx@43dBm (dBc) <-153

1900 Port Frequency Range, Full Band (MHz) 1850-1990 MHz

> Insertion Loss (dB) <0.3 dB Return Loss (dB) >20 dB >54 dB Rejection 824-896 MHz >54 dB Rejection 896-960 MHz >250 W Average Power Handling Peak Power 5 kW IM, 2Tx@43dBm (dBc) <-153

All specifications are subject to change without notice. Contact your Powerwave representative for complete performance data.

Mechanical Specifications

Size, WxHxD (without mounting plate)

Weight Color Housing RF-connectors Mounting Kit Temperature Range **MTBF** Safety

Ingress Protection IP 65 Environmental


4.4" x 6.3" x 3" (112x158x74mm)

2.4 kg (5.3 lbs) Off White (NCS 1502-R) Aluminum, IP 65 DIN 7/16 female

Hose Clamps in Stainless Steel -40 °C to +65 °C 30 Million Hours

EN 60 950, UL 69 950, ETL

EN 60 529 ETS 300 019



Corporate Headquarters

Powerwave Technologies, Inc. 1801 East St. Andrew Place Santa Ana, CA 92705 USA

Tel: 714-466-1000 Fax: 714-466-5800 www.powerwave.com Main European Office Antennvägen 6 SE-187 80 Täby Sweden Tel: +46 8 540 822 00

Fax: +46 8 540 823 40

Hong Kong Office 23 F Tai Yau Building 181 Johnston Road Wanchai, Hong Kong Tel: +852 2512 6123 Fax: +852 2575 4860



©Copyright September 2003, Powerwave Technologies, Inc. All Rights reser









Site Specific Attachments

Site 1


- 1. Site Plans
- 2. Tower Structural Analysis
- 3. Site Photographs


		70	3 5	WIRELESS		2112	ATFORD		BLDG. CODES AND STANDARDS	SUBSCIPACIONES AND SEASON STATEMENT OF CONTRACT MANNO SOURCE BY THE LOCAL AUTHORITY MANNO CHOICS AND STANDARD IN THE LOCA AUTHORITY MANNO SOURCES AND STANDARDS IN EFFECT ON THE UNIT OF CONTRACT MANNO SMALL CONTRACT MANN	HALLIANG CODE: HALLIANG CODE (19C), 20C3 EEFTRICA CODE (20C) HALLIANG CODE (19C), 20C3	MATIONAL TRACTORIA ASSOCIATORI (PRPM) 10 - 2002 INVITUALITY (INTIDAMENTAL PROTECTION COTIF.	HPA 780 - 2000, LIGHTWING PROTECTION CODE	SUBCOMPACTOR'S WORK SWALL COMPLY WITH THE LATEST EXHIGN OF THE FOLLOWING STANDARDS. POLICY OF CHARGE WITHOUTE (ACT) 318, BUILDING CODE REQUIREMENTS	AMERICAN RETIDITE OF STREET CONSTRUCTION (ARC.), MANUAL OF STREET CONSTRUCTION (ARC.), MANUAL OF STREET CONSTRUCTION, ADD, NIVIPH EDITION CONSTRUCTION, ADD, NIVIPH EDITION RESOURCE (ARCANADRE FOR STREET ARCHITACTAL STREAM, STREET ARCHITACTAL STREAM, STREET ARCHITACTAL STREAM, S	STRUCTURES: TIA 607, COMMERCIAL BULDING GROUNDING AND BONDING REQUIREMENTS FOR TREECOMMEMICATIONS	NETHUTE FOR ELECTRICAL AND ELECTRONICS BHONEERS (IEE) 81, GUDE TOR MUSCHARM EARTH RESEARCH, GROUND IMPEDANCE, AND EARTH SURFACE PROTECTION OF A GROUND STATISM PRACTICE FOR POWERING AND GROUNDING EEE TION (1999) RECOMMENDED PRACTICE FOR POWERING AND GROUNDING	OF BLECTRONN: FOURINGHT BEEF ARD AT BEYNLIGHBEN PRACTICES ON STREEF VOLTAGES IN LOW	VICTURE ACTIONS CHARLES FOR LOCATION CAREGORY 'CS' AND "HIGH SYSTEM EXPOSSINE") TO THE TRANSPORT OF 1775 CAREEN INSTALLATION BEGINERARIES	TELUMBA OR-1503, COMMA CASE CONNECTIONS	ANS 11.31, FOR PIRECUM — DC POWER SYSTEMS — TELECOM, EMPHOPMENTAL PROTECTION	TOR ANY CORRESTOR BYTHIS ASSURED AND ASSURED LOADS AND SANDAMAN RECARRING MATERIAL REPORTS SOF CONTRACTORY, OR OTHER REQUIREMENTS. THE WORS PRESENCE REQUIREMENT SALL CORFOR. WHOSE THERE IS CORPLOT BETWEEN A GOREAN. REQUIREMENT AND A SPECIFF REQUIREMENT. THE SPECIFF REQUIREMENT SAME COMERN.		
						SITE NUMBER: 2112	SITE NAME: STRATFORD			Those sets take sort and the true in the properties of the propert	On Rd O J III	58 Strafford	Bridgeport	PROJECT SITE A SINGERIA	135	Fairleid		7 77:E	770 St Michaels 4 100 St	TO TO THE STATE OF	Birds Service Control of the Control	PROJECT SITE STREET	100 Control 100 Co	
									REV	0000	•			•										
APPROVALS) SKIANTIARE OMTE) SICHATURE DATE		SKOMTUNE DATE	з, сомитте	SIGNATURE (MATE		DRAWING INDEX	TITLE SHEET SITE PLAN SITE ELEVATION & ANTENNA PLAN ANTENNA PLIMBING DIAGRAMAL PHA-BETA-CAMMA							-		ORK: UNIMANED TELECOMMUNICATIONS FACILITY MODIFICATIONS : STATTORD			EE: TELECOMMUNCARONS FACURY NAVADO E. 927-07-0 BECKER, LLC		
	NAME (PRINT)	CINGULAR	MME (PRINT)	3	NAME (PRINT)	SITING COUNCE COMMITTEE	MANE (PRINT)	OHER E		2112-11 2112-C1 2112-C2 2112-C3	2112 - C4								SCOPE OF WORK: SITE NUMBER: SITE NAME:	ADDRESS: CITY, STATE ZI. LATITUDE:	LONGITUDE: JURISDICTION: CURRENT USE:	PROPOSED USE: SITE TYPE: RAD CENTER: OWNER:		

SITE NUMBER
2112
SITE NAME:
STRATFORD
SITE ADVERSES
EAST HOMESES
EAST HOMESES
EAST HOMESES

TITLE SHEET

Keingular









October 3, 2005

George Bullock Site Acquisitions, Inc. 184 Rockingham Road Unit A Londonderry, NH 03052 (512) 921-1681 PSG Engineering, Ltd. 245 Commerce Green Blvd. Suite 240

Sugar Land, TX 77478 Phone: (281) 343-7099 Fax: (281) 343-7127

Subject:

Structural Analysis Report

Carrier Designation

Cingular Wireless Co-Locate Carrier Site Number: "2112"

Carrier Site Name: "STRATFORD"

Engineering Firm Designation

PSG Engineering Project Number: 0504A128-A160100

Site Data

623 Honetspot Road, Stratford, CT, Fairfield County Latitude 41°-10'-36.50", Longitude -73°-08'-47.37".

100 Foot - Monopole Tower

Dear Mr. Bullock,

PSG Engineering, Ltd. is pleased to submit this "Structural Analysis Report" to determine the structural integrity of the aforementioned tower. This analysis has been performed in accordance with the terms of Site Acquisitions, Inc. Purchase Order Number *CT-PSG-005*. The purpose of the analysis is to determine the suitability of the tower with the addition of the proposed equipment listed in Table 1 of this report when combined with the existing and reserved equipment on the structure. This analysis has been performed in accordance with the TIA/EIA 222-F standard based upon wind speed condition of 85 mph.

Based on our analysis we have determined the tower and foundation <u>ARE</u> sufficient for the proposed loading provided that the proposed structural modifications are implemented.

We at *PSG Engineering* appreciate the opportunity of providing our continuing professional services to you and Site Acquisitions, Inc. If you have any questions or need further assistance on this or any other projects please give us a call.

Respectfully submitted,

Oscar Pedraza, P.E.

President

TABLE OF CONTENTS

ITRODUCTION
NALYSIS CRITERIA
Table 1 – Proposed Antenna and Cable Information
Table 2 – Installed (I) and Reserved (R) Antenna and Cable Information
Table 3 – Original Tower Manufacturer Design Antenna and Cable Information
NALYSIS PROCEDURE
Table 4 – Documents Provided
Analysis Method
Assumptions
NALYSIS RESULTS
Table 5 – Tower Section Capacity
• •
APPENDIX A
Output from Computer Programs
APPENDIX B
Structural Modification Drawing

INTRODUCTION

This tower was designed by Engineering Endeavors, Inc. on September 10, 1999 per TIA/EIA-222-F using a basic wind speed of 85 mph with ½" radial ice (EEI Drawing #GS51667). The tower was originally designed for an overall height of 90 feet. The tower was extended, based on a 12'-11" extension drawing by Engineering Endeavors dated December 12, 1999 (EEI Drawing #WA11341), to an overall height of 102'-11" to accommodate the existing loading at 100 feet. Foundation comparisons were based on original foundation reactions from the original foundation design by Engineering Endeavors dated October 28, 1999 (EEI Drawing #5553-90).

ANALYSIS CRITERIA

This tower is designed using the TIA/EIA-222-F standard.

The following design criteria apply:

- Basic wind speed of 85 mph.
- Nominal ice thickness of 0.5000 in.
- Ice density of 56 pcf.
- A wind speed of 74 mph is used in combination with ice.
- Deflections calculated using a wind speed of 50 mph.
- · Feedline torque is considered.
- · Pressures are calculated at each section.
- Stress ratio used in tower member design is 1.333

Table 1 - Proposed Antenna and Cable Information

Center Line Elevation (feet)	Number Of Antenna	Antenna Manufacturer	Antenna Model	Mount	Number Of Feed Lines	Feed Line Size (inches)
	6	Da.,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,	7770.00	<u> </u>		
92	6	Powerwave Technologies	LGP21401	-	-	_
	6	recitiologies	LGP13519			

Table 2 - Installed (I) and Reserved (R) Antenna and Cable Information

Center Line Elevation (feet)	Number Of Antenna	Antenna Manufacturer	Antenna Model	Mount	Number Of Feed Lines	Feed Line Size (Inches)
*100	3 (I)	EMS Wireless	RR90-17DP	Flush Mounts (3)	6(I)	7/8 (Internal)
**92	9 (1)	Swedcom	ALP 11011	Platform w/Rails	- m	7/8
32	1(I)	Unknown	3' Whip	(1)	9(I)	(Internal)
80	6 (I)	Decibel	DB844G45	Platform w/Rails	400	1 5/8
	6 (I)	Decidel	DB950F40	(1)	12(I)	(Internal)
72	9 (1)	Decibel	DB950G65VTE	Low Profile Platform (1)	9(1)	1 1/4 (External
58	3 (1)	EMS Wireless	Quad Pol Panel Antennas	Flush Mounts (3)	12(1)	7/8 (Internal)
	1 (l)		15' omni antenna			
26	2 (l)	Standard	10' omni antenna	Standoff T Arms (4)	50	7/8
20	1 (1)	Gianuaru	12' omni antenna	Standoff T-Arm (1)	5(I)	(Internal)
	1 (l)		20' omni antenna			` ′

^{*}Note: All antennas and mounts to be removed from this level. Existing (6) six coax lines to be reused at Ei. 92' level.

^{**}Note: (6) Six existing antennas to be removed and replaced with proposed loads. Remaining (3) three antennas, existing mount and (9) nine coax lines to remain.

Table 3 - Original Tower Manufacturer Design Antenna and Cable Information

Center Line Elevation (feet)	Number Of Antenna	Antenna Manufacturer	Antenna Model	Mount	Number Of Feed Lines	Feed Line Size (inches)
100	3	Unknown	Directional Antennas	8' Low Visibility Antenna Mount		-l
90	12	Unknown	Directional Antennas	10'-8" Standard Platform (1) w/ Corner T-Mounts (3)		
80	12	Unknown	Directional Antennas	10'-8" Standard Platform (1) w/ Corner T-Mounts (3)	Unkn	own
70	12	Unknown	Directional Antennas	10'-8" Standard Platform (1) w/ Corner T-Mounts (3)		
55	1	Unknown	Omni Antenna	6' Antenna Arm (1)	1	
25	6	Unknown	Directional Antennas	Antenna Array Arm (1)	1	

ANALYSIS PROCEDURE

Table 4 - Documents Provided

Document	Remarks	Reference	Source		
Original Tower Manufacturer Drawings	Facility of the Land	EEI Drawing No. GS51667	Engineering Endeavors.		
Tower Extension Drawing	Engineering Endeavors, Inc.	EEI Drawing No. WA11341	Inc.		
Original Foundation Design		EEI Drawing No. 5553-90	1		
Proposed Tower Loading	Cingular Wireless RF Data Sheet	RF Engineer: Francis Malabanan (860.513.7625)	0:: 4 ::::		
Existing Tower Loading	Tectonic Engineering & Surveying Consultants P.C.	W.O. # 2850.CT969	Site Acquisitions, Inc.		

Analysis Methods

ERI Tower (Version 3.0.0.16), a commercially available software program, was used to create a three-dimensional model of the tower and calculate member stresses for various dead, live, wind, and ice load cases. All loads were computed in accordance with the ANSI/EIA/TIA 222F or the local building code requirements. Selected output from the analysis is included in Appendix A.

Assumptions

- 1. Tower and structures were built in accordance with the manufacturer's specifications.
- 2. The tower and structures have been maintained in accordance with manufacturer's specifications.
- The configuration of antennas, transmission cables, mounts and other appurtenances are as specified in Tables 1 and 2.
- 4. When applicable, transmission cables are considered to be structural components for calculating wind loads, as allowed by TIA/EIA-222F.

If any of these assumptions are not valid or have been made in error, this analysis may be affected, and PSG Engineering should be allowed to review any new information to determine its effect on the structural integrity of the tower.


ANALYSIS RESULTS

Table 5 – Tower Section Capacity

Section Number	Elevation (feet)	Percent Capacity Used	Pass / Fail
1	100 - 90	7.4	Pass
2	90 - 45	83.9	Pass
3	45 - 0	77.4	Pass
Base Plate		77.9	Pass
Anchor Bolts		55.0	Pass
Base Foundat	ion (Compared with original design loads)	97.3	Pass

APPENDIX A

Output from Computer Programs



APPURTENANCES

TYPE	ELEVATION	TYPE	ELEVATION
Generic C-2 Lightning Spur	100	(2) DB844G45ZAXY w/Mount Pipe	80
(2) 7770.00 w/Mount Pipe	92	(2) DB950F40T2E-M wMount Pipe	80
(2) LGP2140X (TMA)	92	PIROD 13' Platform w/handrails	80
(2) LGP13519	92	(Monopole)	
ALP 11011-N w/Mount Pipe	92	(2) DB844G45ZAXY w/Mount Pipe	80
(2) 7770.00 w/Mount Pipe	92	(3) DB950G65E-M w/Mount Pipe	72
(2) LGP2140X (TMA)	92	(3) DB950G65E-M w/Mount Pipe	72
(2) LGP13519	92	PIROD 15' Low Profile Platform	72
ALP 11011-N w/Mount Pipe	92	(Monopole)	
(2) 7770.00 w/Mount Pipe	92	(3) DB950G65E-M w/Mount Pipe	72
(2) LGP2140X (TMA)	92	MB72RR65VDPALQ/-R w/Mount Plpe	58
(2) LGP13519	92	MB72RR65VDPALQ/-R w/Mount Pipe	58
ALP 11011-N w/Mount Pipe	92	MB72RR65VDPALQ/-R w/Mount Pipe	58
PIROD 13' Platform w/handrails	90	(2) 10' Whip	26
(Monopole)	180	12' Whip	26
(2) DB950F40T2E-M w/Mount Pipe	80	20' Whip	26
(2) DB844G45ZAXY w/Mount Pipe	80	5' Standoff T-Arm (14' face width)	26
(2) DB950F40T2E-M w/Mount Pipe	80	15' Whip	26

MATERIAL STRENGTH

GRADE	Fy	Fu	GRADE	Fy	Fu
A53-B-35	35 ksi	63 ksi	A572-65	65 ksi	80 ksi

TOWER DESIGN NOTES

- 1. Tower is located in Fairfield County, Connecticut.
- Tower is located in raintell County, Confliction.
 Tower designed for a 85 mph basic wind in accordance with the TIA/EIA-222-F Standard.
 Tower is also designed for a 74 mph basic wind with 0.50 in ice.
 Deflections are based upon a 50 mph wind.
 TOWER RATING: 80.9%



PSG Engineering Ltd. 8206 Forest Gate Drive Sugar Land, Texas

Phone: (281) 343-7099 FAX: (281) 343-7127

Client Site Acquisitions, Inc.	Designed by
Project (2112) (STRATFORD)	Date 16:16:49 10/03/05
Job PSG Engineering Project Number: 0504A100-A160100	Page 1 of 8

Tower Input Data

There is a pole section.

This tower is designed using the TIA/EIA-222-F standard.

The following design criteria apply:

Tower is located in Fairfield County, Connecticut.

Basic wind speed of 85 mph.

Nominal ice thickness of 0.5000 in.

Ice density of 56 pcf.

A wind speed of 74 mph is used in combination with ice.

Temperature drop of 50 °F.

Deflections calculated using a wind speed of 50 mph.

A non-linear (P-delta) analysis was used.

Pressures are calculated at each section.

Stress ratio used in pole design is 1.333.

Local bending stresses due to climbing loads, feedline supports, and appurtenance mounts are not considered.

Tapered Pole Section Geometry

Section	Elevation	Section	Splice	Number	Top	Bottom	Wall	Bend	Pole Grade
		Length	Length	of	Diameter	Diameter	Thickness	Radius	
	ft	ft	ſt	Sides	in	in	in	in	
L1	100'-90'	10'	0'	Round	14.0000	14.0000	0.3750		A53-B-35 (35 ksi)
L2	90'-45'2-13/32"	44'9-19/32"	3'10-3/16"	18	14.0000	26.7925	0.2500	1.0000	A572-65 (65 ksi)
L3	45'2-13/32"-0'	49'19/32"		18	25.1934	40.0000	0.3125	1.2500	A572-65 (65 ksi)

Tapered Pole Properties

Section	Tip Dia.	Area	I_{\perp}	r	С	I/C	J	It/Q	w	w/t
	in	in²	ìn⁴	in	in	in ³	in⁴	in²	in	
L1	14.0000	16.0434	372.7635	4.8232	7.0000	53.2519	744.5114	8.0210	0.0000	0
	14.0000	16.0434	372.7635	4.8232	7.0000	53.2519	744.5114	8.0210	0.0000	0
L2	14.2160	10.9106	260.6108	4.8812	7.1120	36.6438	521.5646	5.4563	2.0240	8.096
	27.2058	21.0615	1874.6054	9.4226	13.6106	137.7314	3751.6774	10.5327	4.2755	17,102
L3	26.7619	24.6788	1930.1638	8.8327	12.7983	150.8145	3862.8674	12.3417	3.8840	12,429
	40.6171	39.3650	7833.4959	14.0891	20.3200	385.5067	15677.2994	19.6863	6.4900	20.768

Tower Elevation ft	Gusset Area (per face)	Gusset Thickness in	Gusset Grade	Adjust. Factor A _f	Adjust. Factor A _r	Weight Mult.	Double Angle Stitch Bolt Spacing Diagonals in	Double Angle Stitch Bolt Spacing Horizontals in
L1 100'-90'		<u></u>		1	1	1		111
L2 90'-45'2-				i	î	î		
13/32"					_	_		
L3 45'2-				1	1	1		
13/32"-0'								

PSG Engineering Ltd. 8206 Forest Gate Drive

Sugar Land, Texas Phone: (281) 343-7099 FAX: (281) 343-7127

Job	Page
PSG Engineering Project Number: 0504A100-A160100	2 of 8
Project	Date
(2112) (STRATFORD)	16:16:49 10/03/05
Site Acquisitions, Inc.	Designed by

Monopole Base Plate Data

Base Plate D	ata
Base plate is square	
Base plate is grouted	√
Anchor bolt grade	A615-75
Anchor bolt size	2.2500 in
Number of bolts	10
Embedment length	60.0000 in
\mathbf{f}_{c}	3 ksi
Grout space	2.0000 in
Base plate grade	A572-60
Base plate thickness	1.7500 in
Bolt circle diameter	48.0000 in
Outer diameter	54.0000 in
Inner diameter	30.0000 in
Base plate type	Stiffened Plate
Bolts per stiffener	1
Stiffener thickness	0.5000 in
Stiffener height	12.0000 in

Feed Line/Linear Appurtenances - Entered As Area

Description	Face or	Allow Shield	Component Type	Placement	Total Number		C_AA_A	Weight
	Leg		7.	ft			ft²/ft	plf
EL. 90' LEVEL								F <i>y</i>
LDF5-50A (7/8 FOAM)	Α	No	Inside Pole	90' - 10'	15	No Ice	0.00	0.33
						1/2" Ice	0.00	0.33
*								
*								
EL. 80' LEVEL	_							
LDF7-50A (1-5/8	В	No	Inside Pole	80' - 10'	12	No Ice	0.00	0.82
FOAM)						1/2" Ice	0.00	0.82
*								
EL. 72 LEVEL								
LDF6-50A (1-1/4	Α	No	CaAa (Out Of	72' - 10'				
FOAM)	A	NO	Face)	12 - 10°	8	No Ice	0.00	0.66
LDF6-50A (1-1/4	A	No	CaAa (Out Of	72' - 10'	1	1/2" Ice No Ice	0.00	1.91
FOAM)	41	NO	Face)	72 - 10	1	No ice 1/2" Ice	0.16 0.25	0.66
*			1 400)			1/2 100	0.23	1.91
*								
EL. 58' LEVEL								
LDF5-50A (7/8 FOAM)	В	No	Inside Pole	58' - 10'	12	No Ice	0.00	0.33
						1/2" Ice	0.00	0.33
*								0.00
*								
EL. 26' LEVEL								
LDF5-50A (7/8 FOAM)	В	No	Inside Pole	26' - 10'	5	No Ice	0.00	0.33
•						1/2" Ice	0.00	0.33
*								
TOWER HARDWARE								
Climbing Ladder (Ar)	С	NT.	C-1-(0-10f	1001 101	_			
Cindonig Laduct (AI)	C	No	CaAa (Out Of	100' - 10'	1	No Ice	0.04	1.00
			Face)			1/2" Ice	0.14	1.53

PSG Engineering Ltd. 8206 Forest Gate Drive Sugar Land, Texas Phone: (281) 343-7099

FAX: (281) 343-7127

Job		Page
PSG Engin	eering Project Number: 0504A100-A160100	3 of 8
Project		Date
1	(2112) (STRATFORD)	16:16:49 10/03/05
Client	Site Acquisitions, Inc.	Designed by

Feed Line/Linear Appurtenances Section Areas

Tower Section	Tower Elevation	Face	A_R	A_F	C _A A _A In Face	C _A A _A Out Face	Weight	
	ft		ft²	fî²	ft ²	fi²	K	
Ll	100'-90'	A	0.000	0.000	0.000	0.000	0.00	
		В	0.000	0.000	0.000	0.000	0.00	
		С	0.000	0.000	0.000	0.375	0.01	
L2	90'-45'2-13/32"	Α	0.000	0.000	0.000	4.154	0.38	
		В	0.000	0.000	0.000	0.000	0.39	
		C	0.000	0.000	0.000	1.680	0.04	
L3	45'2-13/32"-0'	A	0.000	0.000	0.000	5.456	0.38	
		В	0.000	0.000	0.000	0.000	0.51	
		C	0.000	0.000	0.000	1.320	0.04	

Feed Line/Linear Appurtenances Section Areas - With Ice

Tower Section	Tower Elevation	Face or	Ice Thickness	A_R	A_F	C _A A _A In Face	C _A A _A Out Face	Weight
	ft	Leg	in	ft²	ft²	ft²	ft²	K
L1 100'-90'	A	0.500	0.000	0.000	0.000	0.000	0.00	
	В		0.000	0.000	0.000	0.000	0.00	
		C		0.000	0.000	0.000	1.375	0.02
L2	90'-45'2-13/32"	A	0.500	0.000	0.000	0.000	6.834	0.68
		В		0.000	0.000	0.000	0.000	0.39
		С		0.000	0.000	0.000	6.160	0.07
L3	45'2-13/32"-0'	A	0.500	0.000	0.000	0.000	8.976	0.78
	В		0.000	0.000	0.000	0.000	0.51	
		С		0.000	0.000	0.000	4.840	0.05

Feed Line Center of Pressure

Section	Elevation	CP_X	CP_Z	CP_X	CPz
	ft	in	in	Ice in	Ice
T .	1001.001	······································			<u>in</u>
Li	100'-90'	-0.0472	0.0272	-0.1502	0.0867
L2	90'-45'2-13/32"	-0.0452	-0.1193	-0.1464	-0.1267
L3	45'2-13/32"-0'	-0.0343	-0.1441	-0.1164	-0.1821

Discrete Tower Loads

Description	Face or Leg	Offset Type	Offsets: Horz Lateral	Azimuth Adjustment	Placement		C _A A _A Front	C _A A _A Side	Weigh
			Vert ft ft	o	ft		ft²	ft²	K
EL. 90' LEVEL			<i></i>						
LP 11011-N w/Mount Pipe	A	From Leg	4.00	0.0000	92'	No Ice	3.91	6.62	0.04
			0' 0'			1/2" Ice	4.53	7.75	0.09
(2) 7770.00 w/Mount Pipe	Α	From Leg	4.00 0'	0.0000	92'	No Ice 1/2" Ice	5.98 6.44	4.12 4.77	0.05 0.10

PSG Engineering Ltd. 8206 Forest Gate Drive Sugar Land, Texas Phone: (281) 343-7099 FAX: (281) 343-7127

Job		Page
PSG Engine	eering Project Number: 0504A100-A160100	4 of 8
Project		Date
	(2112) (STRATFORD)	16:16:49 10/03/05
Client	Site Acquisitions, Inc.	Designed by

Description	Face or	Offset Type	Offsets: Horz	Azimuth Adjustment	Placement		C _A A _A Front	C _A A _A Side	Weight
	Leg		Lateral Vert						
			ft ft	0	ft		ft²	fì²	K
(2) LGP2140X (TMA)	Α	From Leg	4.00	0.0000	92'	No Ice	1.23	0.37	0.02
		•	0'			1/2" Ice	1.38	0.48	0.02
(2) LGP13519	Α	From Leg	0' 4.00	0.0000	92'	No Ice	0.34	0.21	0.01
		J	0'			1/2" Ice	0.42	0.28	0.01
ALP 11011-N w/Mount Pipe	В	From Leg	0' 4.00	0.0000	92'	No Ice	3.91	6.62	0.04
1201 11011 IV W/Would I spo	Ъ	Trom Log	0'	0.000	92	1/2" Ice	4.53	7.75	0.04
(2) 7770 00 w/M (aunt Dina	n	F I	0'	0.0000	001		# 00		
(2) 7770.00 w/Mount Pipe	В	From Leg	4.00 0'	0.0000	92'	No Ice 1/2" Ice	5.98 6.44	4.12 4.77	0.05 0.10
			0'			1,2 100	0.17	4.77	0.10
(2) LGP2140X (TMA)	В	From Leg	4.00 0¹	0.0000	92'	No Ice	1.23	0.37	0.02
			0'			1/2" Iœ	1.38	0.48	0.02
(2) LGP13519	В	From Leg	4.00	0.0000	92'	No Ice	0.34	0.21	0.01
			0' 0'			1/2" Ice	0.42	0.28	0.01
ALP 11011-N w/Mount Pipe	С	From Leg	4.00	0.0000	92'	No Ice	3.91	6.62	0.04
			0'			1/2" Ice	4.53	7.75	0.09
(2) 7770.00 w/Mount Pipe	С	From Leg	0' 4.00	0.0000	92'	No Ice	5.98	4.12	0.05
•			0'			1/2" Ice	6.44	4.77	0.10
(2) LGP2140X (TMA)	С	From Leg	0' 4.00	0.0000	92'	No Ice	1.23	0.37	0.02
(=, = ===,		210111 206	0'	0,000	72	1/2" Ice	1.38	0.48	0.02
(2) LGP13519	С	Eron I on	0'	0.0000	001	3.T. Y	0.04		
(2) LGF13319	C	From Leg	4.00 0'	0.0000	92'	No Ice I/2" Ice	0.34 0.42	0.21 0.28	0.01 0.01
			0'					7.20	0.01
PiROD 13' Platform w/handrails (Monopole)	С	None		0.0000	90'	No Ice 1/2" Ice	31.30	31.30	1.82
*						1/2 100	40.20	40.20	2.45
* ***EL. 80' LEVEL***									
(2) DB844G45ZAXY	A	From Leg	4.00	0.0000	80'	No Ice	7.71	5.63	0.05
w/Mount Pipe			0'		00	1/2" Ice	8.44	6.73	0.03
(2) DB950F40T2E-M	Α	From Leg	0' 4.00	0.0000	on	37.7.	6.00	6.00	
w/Mount Pipe	A	riom Leg	4.00 0'	0.0000	80'	No Ice 1/2" Ice	6.89 7.56	6.29 7.40	0.05 0.10
•			0'			1,2 100	7.50	7.40	0.10
(2) DB844G45ZAXY	В	From Leg	4.00	0.0000	80'	No Ice	7.71	5.63	0.05
w/Mount Pipe			0' 0'			1/2" Ice	8.44	6.73	0.11
(2) DB950F40T2E-M	В	From Leg	4.00	0.0000	80'	No Ice	6.89	6.29	0.05
w/Mount Pipe			0' 0'			1/2" Ice	7.56	7.40	0.10
(2) DB844G45ZAXY	С	From Leg	4.00	0.0000	80'	No Ice	7.71	5.63	0.05
w/Mount Pipe		J	0'		•	1/2" Ice	8.44	6.73	0.11
(2) DB950F40T2E-M	С	From Leg	0' 4.00	0.0000	80'	No Ice	6.89	6.29	0.05
w/Mount Pipe	J	I TOTAL LANG	0'	0.0000	ου	1/2" Ice	7.56	7.40	0.05
DiDOD 121 Di-45	~	M	0,	0.0000	p. 4.				
PiROD 13' Platform w/handrails (Monopole)	С	None		0.0000	80'	No Ice 1/2" Ice	31.30	31.30	1.82
*						1/2 100	40.20	40.20	2.45

PSG Engineering Ltd. 8206 Forest Gate Drive

Sugar Land, Texas Phone: (281) 343-7099 FAX: (281) 343-7127

Job PSG Engineerii	ing Project Number: 0504A100-A160100	Page 5 of 8
Project	(2112) (STRATFORD)	Date 16:16:49 10/03/05
Client	Site Acquisitions, Inc.	Designed by

Description	Face or Leg	Offset Type	Offsets: Horz Lateral	Azimuth Adjustment	Placement		C _A A _A Front	C _A A _A Side	Weight
			Vert ft ft ft	o	ft		fì²	ft²	K
*									
EL. 72' LEVEL									
(3) DB950G65E-M w/Mount Pipe	A	From Leg	4.00 0' 0'	0,000	72'	No Ice 1/2" Ice	6.89 7.56	5.90 7.01	0.04 0.10
(3) DB950G65E-M w/Mount Pipe	В	From Leg	4.00 0'	0.0000	72'	No Ice 1/2" Iœ	6.89 7.56	5.90 7.01	0.04 0.10
(3) DB950G65E-M w/Mount Pipe	С	From Leg	0' 4.00 0' 0'	0.0000	72'	No Ice 1/2" Ice	6.89 7.56	5.90 7.01	0.04 0.10
PiROD 15' Low Profile Platform (Monopole)	С	None	Ū	0.0000	72'	No Ice 1/2" Ice	17.30 22.10	17.30 22.10	1.50 2.03
*									
EL. 58' LEVEL									
MB72RR65VDPALQ/-R w/Mount Pipe	A	From Leg	1.00 0' 0'	0.0000	58'	No Ice 1/2" Ice	10.50 11.07	6.42 7.37	0.06 0.13
MB72RR65VDPALQ/-R w/Mount Pipe	В	From Leg	1.00 0' 0'	0.0000	58'	No Ice 1/2" Ice	10.50 11.07	6.42 7.37	0.06 0.13
MB72RR65VDPALQ/-R w/Mount Pipe	С	From Leg	1.00 0' 0'	0.0000	58'	No Ice 1/2" Ice	10.50 11.07	6.42 7.37	0.06 0.13
*			V						
*									
EL. 26' LEVEL	~								
15' Whip	С	From Leg	4.00 0' 0'	0.0000	26'	No Ice 1/2" Ice	3.75 5.28	3.75 5.28	0.02 0.05
(2) 10' Whip	С	From Leg	4.00 0' 0'	0.0000	26'	No Ice 1/2" Ice	2.75 3.78	2.75 3.78	0.03 0.05
12' Whip	c	From Leg	4.00 0'	0.0000	26'	No Ice 1/2" Ice	3.60 4.83	3.60 4.83	0.03 0.06
20' Whip	С	From Leg	0' 4.00 0' 0'	0.0000	26'	No Ice 1/2" Ice	6.00 8.03	6.00 8.03	0.04 0.08
5' Standoff T-Arm (14' face width)	С	From Leg	0' 2.67 0' 0'	0.0000	26'	No Ice 1/2" Ice	6.90 8.70	6.90 8.7 0	0.20 0.26
*			v						
TOWER HARDWARE									
Generic C-2 Lightning Spur	A	None		0.0000	100'	No Ice 1/2" Ice	4.00 7.00	4.00 7.00	0.00 0.00

PSG Engineering Ltd. 8206 Forest Gate Drive Sugar Land, Texas Phone: (281) 343-7099 FAX: (281) 343-7127

Job	Page
PSG Engineering Project Number: 0504A100-A160100	6 of 8
Project	Date
(2112) (STRATFORD)	16:16:49 10/03/05
Client Site Acquisitions, Inc.	Designed by

Load Combinations

Comb.	Description
No.	
1	Dead Only
2	Dead+Wind 0 deg - No Ice
. 3	Dead+Wind 30 deg - No Ice
4	Dead+Wind 60 deg - No Ice
5	Dead+Wind 90 deg - No Ice
6	Dead+Wind 120 deg - No Ice
7	Dead+Wind 150 deg - No Ice
8	Dead+Wind 180 deg - No Ice
9	Dead+Wind 210 deg - No Ice
10	Dead+Wind 240 deg - No Ice
11	Dead+Wind 270 deg - No Ice
12	Dead+Wind 300 deg - No Ice
13	Dead+Wind 330 deg - No Ice
14	Dead+Ice+Temp
15	Dead+Wind 0 deg+Ice+Temp
16	Dead+Wind 30 deg+Ice+Temp
17	Dead+Wind 60 deg+Ice+Temp
18	Dead+Wind 90 deg+Ice+Temp
19	Dead+Wind 120 deg+Ice+Temp
20	Dead+Wind 150 deg+Ice+Temp
21	Dead+Wind 180 deg+Ice+Temp
22	Dead+Wind 210 deg+Ice+Temp
23	Dead+Wind 240 deg+Ice+Temp
24	Dead+Wind 270 deg+Ice+Temp
25	Dead+Wind 300 deg+Ice+Temp
26	Dead+Wind 330 deg+Ice+Temp
27	Dead+Wind 0 deg - Service
28	Dead+Wind 30 deg - Service
29	Dead+Wind 60 deg - Service
30 31	Dead+Wind 90 deg - Service
31	Dead+Wind 120 deg - Service
32 33	Dead+Wind 150 deg - Service
33 34	Dead+Wind 180 deg - Service Dead+Wind 210 deg - Service
34 35	
36	Dead+Wind 240 deg - Service Dead+Wind 270 deg - Service
30 37	Dead+Wind 300 deg - Service
38	Dead+Wind 330 deg - Service
	Dead. Willia 350 tag - Bel vice

Maximum Tower Deflections - Service Wind

Section	Elevation	Horz.	Gov.	Tilt	Twist
No.		Deflection	Load		
	ft	in	Comb.	0	0
Ll	100 - 90	19.615	36	1.6596	0.0024
L2	90 - 45.2005	16.142	36	1.6546	0.0024
L3	49.0495 - 0	4.497	36	0.8967	0.0024

PSG Engineering Ltd. 8206 Forest Gate Drive

Sugar Land, Texas Phone: (281) 343-7099 FAX: (281) 343-7127

Јов PSG Engineering Project Number: 0504A100-A160100	Page 7 of 8
Project (2112) (STRATFORD)	Date 16:16:49 10/03/05
Site Acquisitions, Inc.	Designed by

Critical Deflections and Radius of Curvature - Service Wind

Elevation	Appurtenance	Gov.	Deflection	Tilt	Twist	Radius of
		Load				Curvature
ft		Comb.	in	٥	0	ft
100'	Generic C-2 Lightning Spur	36	19.615	1.6596	0.0024	19393
92'	ALP 11011-N w/Mount Pipe	36	16.831	1.6625	0.0024	12130
90'	PiROD 13' Platform w/handrails	36	16.142	1.6546	0.0024	9724
	(Monopole)					
80'	(2) DB844G45ZAXY w/Mount Pipe	36	12.792	1.5393	0.0024	4932
72'	(3) DB950G65E-M w/Mount Pipe	36	10.282	1.3825	0.0024	3540
58'	MB72RR65VDPALQ/-R w/Mount	36	6.448	1.0658	0.0024	2368
	Pipe					
26'	15' Ŵhip	35	1.446	0.7524	0.0024	3686

Maximum Tower Deflections - Design Wind

Section	Elevation	Horz.	Gov.	Tilt	Twist	
No.		Deflection	Load			
	ft	in	Comb.	0	۰	
L1	100 - 90	56.490	11	4.7830	0.0073	
L2	90 - 45.2005	46.492	11	4.7686	0.0073	
L3	49.0495 - 0	12.953	11	2.5843	0.0071	

Critical Deflections and Radius of Curvature - Design Wind

Elevation	Appurtenance	Gov.	Deflection	Tilt	Twist	Radius of
Δ		Load		٥	_	Curvature
		Comb.	in		0	ft
100'	Generic C-2 Lightning Spur	11	56.490	4.7830	0.0073	6847
92'	ALP 11011-N w/Mount Pipe	11	48.474	4.7889	0.0073	4281
90'	PiROD 13' Platform w/handrails	11	46.492	4.7686	0.0073	3430
	(Monopole)					2 .0 3
80'	(2) DB844G45ZAXY w/Mount Pipe	11	36.846	4.4713	0.0074	1731
72'	(3) DB950G65E-M w/Mount Pipe	11	29.616	4.0551	0.0074	1239
58'	MB72RR65VDPALQ/-R w/Mount	11	18.574	3.1494	0.0073	826
	Pipe				0.007,5	020
26'	15' Whip	10	4.164	1.5682	0.0054	1280

Base Plate Design Data

Plate	Number		Actual	Actual	Actual	Actual	Controlling	Critical
Thickness in	of Anchor Bolts	Size -	Allowable Ratio Bolt Tension K	Allowable Ratio Concrete Stress ksi	Allowable Ratio Plate Stress ksi	Allowable Ratio Stiffener Stress ksi	Condition	Ratio
1.7500	10	2.2500	93.56 174.90 0.53	1.421 2.100 0.68	46.710 45.000 1.04	14.204 45.000 0.32	Plate	1.04

ERITower

PSG Engineering Ltd. 8206 Forest Gate Drive

Sugar Land, Texas Phone: (281) 343-7099 FAX: (281) 343-7127

Job		Page
PSG Engi	neering Project Number: 0504A100-A160100	8 of 8
Project	(2112) (STRATFORD)	Date 16:16:49 10/03/05
Client	Site Acquisitions, Inc.	Designed by

Compression Checks

			Pole	Des	sign D	ata				
Section No.	Elevation	Size	L	L _u	Kl/r	F_a	A	Actual P	Allow.	Ratio P
	ft		ft	ft		ksi	in ²	K	K	
L1	100 - 90 (1)	TP14x14x0.375	10'	0'	0.0	21.000	16.0434	-1.51	336.91	0.004
L2	90 - 45.2005 (2)	TP26.7925x14x0.25	44'9- 19/32"	0'	0.0	39.000	20.1894	-9.68	787.38	0.012
L3	45.2005 - 0 (3)	TP40x25.1934x0.3125	49'19/32"	0'	0.0	39.000	35.8035	-15.56	1396.34	0.011


	Pole Bending Design Data										
Section No.	Elevation ft	Size	Actual M _x kip-fi	Actual f _{bx} ksi	Allow. F _{bx} ksi	Ratio f _{bx} F _{bx}	Actual M _y kip-ft	Actual f _{by} ksi	Allow. F _{by} ksi	Ratio f _{by} F _{by}	
L1	100 - 90 (1)	TP14x14x0.375	7.79	-1.755	23.100	0.076	0.00	0.000	23.100	0.000	
L2	90 - 45.2005 (2)	TP26.7925x14x0.25	438.42	-41.586	39.000	1.066	0.00	0.000	39.000	0.000	
L3	45.2005 - 0 (3)	TP40x25.1934x0.3125	1028.18	-38.719	39.000	0.993	0.00	0.000	39.000	0.000	


		Pol	e Inter	action	Desig	n Data		
Section No.	Elevation	Size	Ratio P	Ratio f _{bx}	Ratio f _{by}	Comb. Stress	Allow. Stress	Criteria
	ft		$\overline{P_a}$	$\overline{F_{bx}}$	F_{by}	Ratio	Ratio	
L1	100 - 90 (1)	TP14x14x0.375	0.004	0.076	0.000	0.080	1.333	H1-3
L2	90 - 45.2005 (2)	TP26.7925x14x0.25	0.012	1.066	0.000	1.079	1.333	H1-3
L3	45.2005 - 0 (3)	TP40x25.1934x0.3125	0.011	0.993	0.000	1.004	1.333	H1-3


			Section Cap	acity T	able			
Section No.	Elevation ft	Component Type	Size	Critical Element	P K	SF*P _{allow}	% Capacity	Pass Fail
L1	100 - 90	Pole	TP14x14x0.375	1	-1.51	449.10	6.0	Pass
L2	90 - 45.2005	Pole	TP26.7925x14x0,25	$\tilde{2}$	-9.68	1049.58	80.9	Pass
L3	45.2005 - 0	Pole	TP40x25.1934x0.3125	3	-15.56	1861.32	75.3	Pass
							Summary	
						Pole (L2)	80.9	Pass
						Base Plate	77.9	Pass
						RATING =	80.9	Pass

APPENDIX B

Structural Modification Drawing









Site Specific Attachments

- 1. Site Plans
- 2. Tower Structural Analysis
- 3. Site Photographs

	Cingular	WEIES			_				15 S	STANFORD - CENTRAL SET NAME: STANFORD - CENTRAL SET ADDRESS:	SAMPORD, CT. (TITLE SHEET
				WIRELESS		2118	D. CENTRAI		DI DC COOPER AND COLUMN	BLLUG. CALLES AND STANDARDS SECRETARISE SECRETARIAN SERVICES FROM STATE OF THE LOCA ARRIVED FROM SECRETARIA SE	ALLING CORE MITOWAY READER CORE (MC), 2003 DETENDAL CORE MITOWAY REPRESENTANCE OF THE STATE O	T GONGRAL CORRES CORRECCORRES CORRECCORRES
						SITE NUMBER: 2118	SITE NAME: STAMFORD - CENTRAL		MAPS & DIRECTIONS	RALDHE, STE G OR SH FLORE.	Wonklyon AVCINITY MAP	Highland Nie Paymond Stymphond Stymp
									REV		- AICINILA NVB	SITE MAP
APPROVALS	SCHATURE DATE		SCHATURE		3tot 3tot 3tot 3tot 3tot 3tot 3tot 3tot	COMMITTEE	THE TRACKS		DRAWING INDEX	TITLE SHEET SITE PLAN SITE ELEVATION & ANTENNA PLAN ANTENNA PLUMBRIG DIAGRAMA LHA.BETA.GAMMA		
	MAC (PRINT)	DOLA	(base) Swa	3	POSE (PRINT)	STING COUNCIL COMMITTEE	made (PRSM)	S		218-17 218-0 218-0 218-0	SCOPE OF WINN STEP AND STEP AN	LOTINOS MASOCINOS MASOCINOS MASOCINOS MASOCINOS MASOCINOS SIT 179E





Demirtas C. Bayar, P.E.

October 7, 2005

Mr. George Bullock SAI Communications 184 Rockingham Road, Unit A Londonderry, NH 03053

Re: Structural Analysis of tower in Stamford, CT. BE Job No. 0509-2

Dear Mr. Bullock,

Our previous analysis of the tower in 2000 was for the tower to carry the following antennas:

a). 9 - ALP9212 antennas above the top deck.

- b). 1 10' diameter parabolic antenna 8' below the top deck.
- c). 3 Cellular antennas at the B1-B1 level.
- d). 16 Cell antennas at the D-D level for Metricom. This was not done and not included in design.

Our new analysis assumed the following antennas and equipment to be carried by the tower:

- a). 6 Powerwave 7770 antennas with 12 Powerwave TMA above the top deck to replace the existing ALP antennas. The wind area of this equipment is larger than the 9 ALP antennas.
- b). 1-10' diameter parabolic antenna 8' below the top deck.
- c). 6 Cellular antennas on 3 frames at the B1-B1 level. The 3 additional antennas and their frames were not included in our last analysis.
- d). 3 Frames for future antennas at the B2-B2 level. These were not included in previous analysis.

The proposed configuration will result in a larger total wind load above the D-D level than the previous analysis. This then will require an alteration to the existing structure. The alteration will consist of replacing all the end connections of the diagonal members with A325 bolts between the D-D level and the G-G level. Sketch No. 0509 indicates this work.

Additionally we recommend that the antenna frames at the B2-B2 level be removed. These do not carry any antennas.

Once this alteration is done the structure will be adequate to support the proposed new antenna configuration stated above.

Yours truly,

Demirtas Bayar, P.E.#, 12725 (CT)

President

RY.	YAR	ENGINEERING, P.C.		SKETCH NO
PRO	JECT .	STAMFORD, CT. EX	ISTING 125'-0" TYPE 'K'	Date <u>10/6/2005</u> ———————————————————————————————————
		V = 115 mph (3-SEC GUST) I = 1.15 (CATEGORY III) Kd = 0.85	EXISTING ANTENNAS	REPLACEMENT ANTENAS
7	7/1 11-74	A-A LEVEL		+12-POWERWAVE 7770
	16'-5 1/8"	A1-A1 LEVEL 230'-0" A2-A2 LEVEL 221'-0" B-B LEVEL 220'-0"	10' DISH	
	13'-6 7/8"	B.L. 81-BI LEVEL 213'-6 7/8' 82-82 LEVEL 209'-0 7/8' C-C LEVEL 50	6-CELLS ON FRAMES	(REMOVE)
	T	C1-C1 LEVEL		•
	100"	E-E TEAET	ALS BY REPLACING	
125'-0"	10,-0"	E1-E1 TEAST 170'-0	OF DIAGONA	
	10,-0_	F-F LEVEL	REINFORCE CONNECTIONS EXISTING END BOLTS	
		G-C LEAST "0-'0"	REINFO	
		G1-G1 LEAET	_	
	80	TOP OF BASE PLATE TOP OF ROOF SLAB ELEVATION	_	Lamin May ar



Site Specific Attachments


- 1. Site Plans
- 2. Tower Structural Analysis
- 3. Site Photographs


		70	22	WIRELESS		: 2124	RY CENTRAL	1000	BLDG. CODES AND STANDARDS	THES CHAMP LEMELINGO JO 30M 3H, NO 123420 IN SCHIPINIZIS (DIV SSICIO THE COLLICION FOR 3H, SO MULICIA 3H, TRUCHOTI 3H, SACO PROTI CHE CHE STREET STRE	COVERN THE DESIGN. BUILDING CODE. DITERALITME BUILDING CODE.	ELECTRICAL CODE: HATICHAL FIRE PROTECTION ASSOCIATION (NFFA) 70 - 2002 NATIONAL BLEFTIESD; CODE	LICHTRING PROTECTION CODE: NFPA 780 - 2000, LIGHTRING PROTECTION CODE	SUBCOMPRACTICE'S WORK SHALL COMPLY WITH THE LATEST ELETION OF THE FOLLOWING STANDARDS.	AMENAN CHOKER, ENGINE (AC) 319, BALDNE COC ESTINEMENTS THE STRUCTURE, CONCISES CONSTRUCTION (AGC), MANUL OF STEEL CONSTRUCTION, KOS, WITHIN EDITOR (TA) 222-F, STRUCTURA, ELEDAMANICHORS MOSSIAT ASSOCIATION (TA) 222-F, STRUCTURA.		NSTRUTE FOR ELECTRICAL, AND ELECTROANTS BRIGHEEDS (EEE) 81, GLIDE. FOR MEISURING ENTH RESISTANT, GROUND MFEDANCE, AND EARTH SURPACY POTENINES, OF A GROUND SSTELL FEET 1100 (1988) RECEMBENEED PRACTICE FOR PORTERE, AND STOCKHAMEN	OF ELECTRONIC EQUIPMENT	KEE CAZAI, RECOMMENDED PRACTICES ON SURGE VOLTAGES IN LOW VOLTAGE AC POWER CHOLARTS (FOR LOCATION CATEGORY TOT AND "HEN STSTEM EXPOSINE")	TRICORDA GR-1275, GENERAL INSTALLATON RECUMEMENTS TRICORDA GR-1503, COAXIAL CIBLE CONNECTIONS	AKS 11.311, FOR TELECOM — DC POWER SYSTEMS TELECOM, ENHIONMERTAL PROTECTION	FOR ANY CONFLICTS RETWEEN SECTIONS OF LISTED CODES AND STANDARDS RECHREMENTS, OR OTHER REGULREMENTS, THE ADDRESS TRAINING REQUIREMENTS SAFETY FOR THEIR THEIR THE CONFINE THE THEIR THEIR CONFLICTS RETWEEN A CAPERRY RECURREMENT AND A STREAM OF THE THEIR THEIR A CAPERRY REQUIREMENT AND A STREAM.	THE SPECIFIC REQUIREMENT SMALL COMERN.		
			るころこと			SITE NUMBER: 2124	SITE NAME: DANBURY CENTRAL		MAPS & DIRECTIONS	FROM WARTDOOD, CT. TRANEJ REST ON 1—84 APPROMANTELY SO MIGES TO DANIBURY (SOT 5), AT END OF WART REST ON THOUSE WAS NOT SOME THE WART OF THE WART OF THE STATE OF	(62) Putham Lake		NIC SEATOWN	Danbury evolectism 302	PUTNAM PLANTING PALICE PRINTED BERTHEIL	marks th	Waccabur 116	のでは、100mmのでは、100mmのでは、100mmのでは、100mmのでは、100mmのでは、100mmのでは、100mmのでは、100mmのでは、100mmのでは、100mmのでは、100mmの		The state of the s			PROJECT SITE	THE TO STORY	
									REV	00															
	OATE		PATE		DATE		DATE				·								ñ						
APPROVALS	SIGNATURE		SIGNATURE		SKAKTURE	WANTEE	SIGNATURE		DRAWING INDEX	TITLE SHEET EQUIPMENT ROOM PLAN	SHE FLAN ELEVATION ANTENNA PLUMBING DIAGRAM	RF DATA INFORMATION						PROJECT INFORM	[39 WEST ST DANBURY, CT 06810 41,3926 N	73,4544" W FAIRELD COUNTY TO COOLUMN STORES	TELECOMMUNICATIONS FACILITY TI 69°	SNET		
	NAME (PRINT)	CINGULAR	NAME (PRINT)	3	NAME (PRINT)	STING COUNCIL COMMITTEE	WAME (PIRMT)	OTHER		2124 - 71	727 727 727 727 727 727 727 727 727 727	2124 - C5					•		SCOPE OF WORK: STE NUMBER: STE NAME:	ADDRESS: CITY, STATE ZIP LATITUDE:	LONGITUDE: JUNISDICTION:	PROPOSED USE: SITE TYPE: RAD CENTER:	OWNER:		NAC C/KS


STE NUMER
2124
STE NAME
STE NAME
STE NAME
STE ANDERSS
30 WEST ST.
DANBURY, CT 08810

TITLE SHEET

Keingular







Demirtas C. Bayar, P.E.

October 13, 2005

Mr. George Bullock SAI Communications 184 Rockingham Road, Unit A Londonderry, NH 03053

Re: Analysis of structures at Bridgeport, CT. (Site 2176) and Danbury CO., CT (Site 2124) BE Job No. 0509-6 & 0509-3

Dear Mr. Bullock,

Bridgeport, CT.:

The pipe supports for the antennas extend 4'-3" above the parapet wall of the building roof at 430 John Street, Bridgeport, CT. This works well with the existing Cellwave antenna which is 4'-0" long. The Powerwave 7770 antenna which will replace the existing is 4'-7" long. The new antenna may require an extension pipe attached to the existing pipe if the mounting of the new antenna will not work with the 4'-3" pipe extension. We checked the strength of the pipe and its connections based on an additional 3" diameter pipe support as well the 7770 antenna plus TMAs on the back of the antenna and found that the system is adequate to support the loads.

Danbury CO, CT.:


Replacement of the 3 existing antennas with 3 Powerwave 7770 antennas under the shroud of the structure on top of the roof at 39 West Street, Danbury, CT will not change the total loads on the structure. However, we assumed that the antennas will be longer and thus add wind area plus the TMAs will add wind area. The existing structure will be adequate to support the assumed loads and the proposed configuration of the equipment.

Yours truly,

Demirtas Bayar, P.E. # 12725 (CT)

Demitas Ikayan

President



Site Specific Attachments

- 1. Site Plans
- 2. Tower Structural Analysis
- 3. Site Photographs

	•	\ (\frac{1}{2}\)	בפ	WIRELESS		2133	RY SOUTH		BLDG. CODES AND STANDARDS	SIBCOMPACTOR'S WORK SHALL COMPLY WITH ALL MPDICABLE, NATIONAL, STATE, and D.COLV, CORES AS ADOPTED BY THE LOCAL ARTHORITY HAWNED AUSSCHOOM, (AND TOR HE COCKION, THE EDRING OF THE ANA ADOPTED AUSSCHOOM OF MICHAEL ON HE DRE OF COMPACT MAND SHALL	WITIDING CODE	INITIONALINAL PROLING COR. (BC), 2003 INITIONAL TORE ROTECTION ASSOCIATION (RFPA) 70 – 2002 MATONN, EEECTRICK, CODE	LIGHTANO PROTECTION CODE: NFPA 780 2000, LIGHTNING PROTECTION CODE	Subcontractor's work shall comply with the latest edition of the following standards. American concrete institute (ACL) 318, Barding code recurrenents	FOR STRUCTURAL CONCRETE AMERICAN HISTORY OF STEEL CONSTRUCTION (AISC), MANUAL OF STEEL CONSTRUCTION, ASO, INN'IN EDITION TELECOMMUNICATIONS INDIGERY ASSOCIATION (III) 2722—F. STRUCTURAL	STANDAROS FOR STEEL ANTENNA TOMER AND ANTENNA SUPPORTING TOMESTORES OF STEEL ANTENNA GROUNDING AND BONDING REGUREMENTS FOR TELECOMMANICATIONS	institute for electrical, and electromes encayers (feee) by, guide For impassing eath resistint, ground impedance, and eath surface potentials of a ground system	ILEE TOO (1999) RECOMMENDED PROCINCE FOR POWERING AND GROUNDING OF ELECTRONIC EQUIPMENT	ree c62.41, recommended ppactaces on surge voltages in low voltage ac pomer crecuts (for location caegory "C3" and "high system exposure")		TELCORDA GR-1503, CONCAL CABLE CONNECTIONS AND 17-181 FOR THEFORM - DF ROWER SYSTEMS - TELEFORM	TAL PROTECTION - DE FOREN SISIEMS TAL PROTECTION SEPTONS OS LISTER O	IG MATERIAL, METHOD T RESTRICTIVE REQUI	ITE SYCUTY RECORDERN SYNCE GOVERN		
			ロコココント			SITE NUMBER: 2133	SITE NAME: DANBURY SOUTH		MAPS & DIRECTIONS	PROW I—84 EAST TAKE ENT 3 86AR RIGHT ONTO US—7 SOUTH. BEAR LETT ONTO STARRS PLAIN RD. BEAR INCOMINE STIE IS TO THE LEFT.	188 22 54 39 37 6	Brokysjer 6.3 Danbury 6.1 C U			310 K. F. L. K. K. L. K. L. K. K. K. K. L. K.	Salem 116 Salem	121 FRedding Wilsboro (122) Projection					PROJECT SITE	7 Danbury	om	Mooster Mooster	Mountain mismon
									REV	. 00																
APPROVALS	SIGNATURE DATE		SIGNATURE DATE		SIGNATURE DATE	СОМИПТЕЕ	SIGNATURE DATE		DRAWING INDEX	TITLE SHEET EQUIPMENT PLAN STEET EXATION E ANTENNA DI AN	ANTENNA PLUMBING DIAGRAM-ALPHA-BETA-GAMMA RF DATA INFORMATION												LATING 65-0 RCC CONSULTANTS			
	HAME (PRINT)	CINGULAR	NAME (PRINT)	3	NAME (PRINT)	SITING COUNCIL COMMITTEE	NAME (PRINT)	OTHER		2133 - T1 2133 - C1 2133 - C1	2133 - C3								SCOPE OF WORK: SITE NUMBER: SITE NAME:	ADDRESS: CITY, STATE ZIP	LONGITUDE:	JURISDICTION: CURRENT USE: PROPOSED USE:	SITE TYPE: RAD CENTER: OWNER:			








SITE FILMBER:
2133
SITE NAME:
DANBURY - SOUTH
SITE ADDRESS:
NOOSES WOUNTAN
DANBURY, CT






TITLE SHEET

SPEET PLANBER





Demirtas C. Bayar, P.E.

October 15, 2005

Mr. George Bullock SAI Communications 184 Rockingham Road, Unit A Londonderry, NH 03053

Re: Structural Analysis of tower in Moses Mountain, CT. (Site 2133) BE Job No. 0509-5

Dear Mr. Bullock,


Our previous analysis of the existing 65'-0" tower at Moses Mountain, Danbury, CT. in 2003 was for the tower to carry the antennas and equipment shown on Sketch No SK0509-4. That analysis included the 12 ALP antennas which now will be replaced by 6 powerwave 7770 antennas and 12 powerwave TMAs. The number of cables running down the tower will be the same. That previous analysis required substantial strengthening. The new members installed at that time were designed for strength as well as the reduction of the tilt and twist of the tower. Our analysis of your proposed antenna configuration shows that the tilt and twist of the tower will be within acceptable limits and the strength of the members is adequate to support the loads produced by the antennas and equipment shown on the attached sketch.

This last analysis assumes that the number of cables will remain the same and no new cable racks will be installed on the tower.

Yours truly,


Demirtas Bayar, P.E. # 12725 (CT)

President



2133








Site Specific Attachments

- 1. Site Plans
- 2. Tower Structural Analysis
- 3. Site Photographs

	CINGUIAL	>		communications	-		PSC ENGINEERING, U.O.		STE NUMBER:	STE. NAME: BRIDGEPOYT - CENTRAL STE ADRESS:	BEDGINORY, CT	THE A WOLATCH OF THE PROPUEDTINY ROUTS DOCUMENT WALKET HER ARE THE PROPULATION ACTIVE UNIQUE THE JANESCON OF A DOCUMEN	COMMING OF THE COMMISSION OF T	1.11	MANAGET NC. OBDANTA-DBB159 SUGNITIALS SUGNITIALS TO DESCRIPTION	80/11/90 W MD 22419900 0445 1				-		0 000 mm m	TITLE SHEET		SHEET NUMBER	F
	•	10	5	WIRELESS	(1	9/17	RT - CENTRAL		BLDG. CODES AND STANDARDS	CODES HIS RESION. SINGCOMMENTALS IN ELECT ON THE DIRE OF CONTRACT MAND SHALL CONTRACT SAME SHALL CONTRACT OF SHALL CONTRACT S	BULDNO CODE:	RECTRICAL CODE: NATIONAL CODE: NATIONAL FIRE PROJECTION ASSICIATION (NPPA) 70 – 2002 NATIONAL	LUGATINAG PROTECTION CODE: NFPA 780 – 2000, LGHTANG PROTECTION CODE	SUBCOMPACTOR'S MORE SAUL COURTY WITH THE LATEST EDITION OF THE POLICY STANDARDS.	MARROWN CONTRILE NISTUTE (AC) 314. BULDING CODE REQUIREMENTS FOR STRUCTURAL CONTRILE AMERICAN INSTITUTE OF STEEL CONSTRUCTION (ASIC), LANGUA, OF STEEL TO STRUCTURAL STEEL STEEL CONSTRUCTION (ASIC), LANGUA, OF STEEL THE STRUCTURAL STEEL STEEL STRUCTURAL	STRUCTURES. PROSTER ASSOCIATION (194 4.62-4; INTRO-UNIVERSITY STRUCTURES. STRUCTURES. ATTEMN TODAY AND ATTEMN SEPONTINE. STRUCTURES. ATTEMN TODAY AND BATCHING REQUIREMENTS FOR TRACES, OFFICIAL BALLING GROUNDING AND BATCHING REQUIREMENTS FOR TRACES, OFFICIAL REQUIREMENTS.	NSTRUTE FOR ELECTRICAL AND ELECTRONICS ENCAREDIS (FEE) 81, GUICE FOR ACCIONNESS FOR AND ENTRY SAFENCE. FOR ACCIONNESS FOR A SAFENCE FOR A 11 AT A COMMUNICATION FOR THE SAFENCE FOR SAFENC		REF COLLA, PRODMENUED PANETICES ON STIRE VOLVAES IN LOW SYSTEM ENFORME, OFFI (COLTAIN CATEGORY "CS" AND "HIGH SYSTEM ENFORME")	TELCORDA GR-1275, GBREMA, RYSTALLATION REQUIREMENTS TELCORDA GR-1501, COUNK, CARLE COMPECTIONS	ANS 71.311 ENARCHAEN	FOR ANY COMPLICIS BETWEEN SCENEDS OF LISTED CODES AND STAMBURES. RECEIPINGS OF CONSTRUCTION, NO FURSH SCUREDERFINS, THE WOST RESTRUCTIVE REQUERIENT SMALL CONTENT, RECEIPINGS.	СОМИЈУ ВТИБВИ А СВЕРИ, ИБДИВЈЕМ МО А SPEJIK, REGUREJEM, TRE SPEJIK REGUREJEM SAML, COVERN,			
						OILE NOMBER: 21/6	SITE NAME: BRIDGEPORT - CENTRAL		MAPS & DIRECTIONS	I TIME 1-45 EAST AND TAKE DAT 27A ONTO SN-25 (SR-45) NORTH. TAKE DAT 2 AND GEAR RIGHT ONTO MORRISON ST. TURN RIGHT ONTO FARMERED ANE.	(3) Trumbull (3) F C Trumbull (3)	100 March 100 Ma	Muck of Real Real Real Real Real Real Real Real	NITE OF THE PROPERTY OF THE PARTY OF THE PAR	11	Westport Cawellia			The second secon		The state of the s	N N D ON D SKERE WAS BEEN BEEN BEEN BEEN BEEN BEEN BEEN BEE	TIS TO THE TANK THE TO THE TANK THE TIS TO THE TANK THE TIS TO THE TANK THE TIS TO THE T	AVE	istan To	
APPROVALS	SIGMATIBE DATE		SYCHATURE DATE		зилине оме	CAMITIE	SOWITHE		DRAWING INDEX REV	TITLE SHEET 0 SITE PLAN 0 0	AGRAM-ALPHA-BETA-GANNA	RF DATA INFORMATION 0							l			TELECOMMUNICATIONS FACULY TELECOMMUNICATIONS FACULY ROGETOP				
	NAME (PRONT)	CINGULAR	NAME (PRENT)	35	NAME (PRINT)	STING COUNCE COMMITTEE	NAME (PRINT)	отнея		2176 - T1 2176 - C1 2176 - C2	2176 - C3 2176 - C4	2176 - C5							SCOPE OF WORK: SITE NUMBER: SITE NAME:	ADDRESS: CITY, STATE ZIP LATTRIDE:	LONGITUDE: JURISDICTION:	CURRENT USE: PROPOSED USE: SITE TIPE:	RAO CENTER: OWNER:			







Demirtas C. Bayar, P.E.

October 13, 2005

Mr. George Bullock SAI Communications 184 Rockingham Road, Unit A Londonderry, NH 03053

Re: Analysis of structures at Bridgeport, CT. (Site 2176) and Danbury CO., CT (Site 2124) BE Job No. 0509-6 & 0509-3

Dear Mr. Bullock,

Bridgeport, CT.:

The pipe supports for the antennas extend 4'-3" above the parapet wall of the building roof at 430 John Street, Bridgeport, CT. This works well with the existing Cellwave antenna which is 4'-0" long. The Powerwave 7770 antenna which will replace the existing is 4'-7" long. The new antenna may require an extension pipe attached to the existing pipe if the mounting of the new antenna will not work with the 4'-3" pipe extension. We checked the strength of the pipe and its connections based on an additional 3" diameter pipe support as well the 7770 antenna plus TMAs on the back of the antenna and found that the system is adequate to support the loads.

Danbury CO, CT.:


Replacement of the 3 existing antennas with 3 Powerwave 7770 antennas under the shroud of the structure on top of the roof at 39 West Street, Danbury, CT will not change the total loads on the structure. However, we assumed that the antennas will be longer and thus add wind area plus the TMAs will add wind area. The existing structure will be adequate to support the assumed loads and the proposed configuration of the equipment.

Yours truly,

Demirtas Bayar, P.E. # 12725 (CT)

Demilas I Bayan

President



Letters to Chief Elected Officials



Honorable Joseph G. Crudo, Town Council Chairman Town of Stratford Town Hall 2725 Main Street Stratford, CT 06615

Re: Notice of Exempt Modifications to Various Facilities in the Towns of Stratford, Stamford, Danbury and Bridgeport, Connecticut

Dear Mr. Crudo,

As part of its merger and integration efforts, New Cingular Wireless PCS, LLC ("Cingular" or "the Company") intends to modify instrumentation and/or antenna configurations at certain wireless telecommunications facilities. As required by the Regulations of Connecticut State Agencies ("R.C.S.A.") Section 16-50j-73, the Connecticut Siting Council has been notified of the changes and will review the Company's proposal. Please accept this letter and attachments as notification under Section 16-50j-73 of construction which constitutes an exempt modification pursuant to R.C.S.A. Section 16-50j-72(b)(2).

The accompanying letter fully describes Cingular's proposal. However, if you have any questions or require any further information on our plans or the Siting Council's procedures, please call me at (860) 301-6378 or Mr. Derek Phelps, Executive Director, Connecticut Siting Council at (860) 827-2935.

David S. Malko, P.E.

Consultant for New Cingular Wireless



Honorable Dannel P. Malloy, Mayor City of Stamford 10th Floor Govt Ctr. 888 Washington Blvd. Stamford, CT 06902

Re: Notice of Exempt Modifications to Various Facilities in the Towns of Stratford, Stamford, Danbury and Bridgeport, Connecticut

Dear Mr. Malloy,

As part of its merger and integration efforts, New Cingular Wireless PCS, LLC ("Cingular" or "the Company") intends to modify instrumentation and/or antenna configurations at certain wireless telecommunications facilities. As required by the Regulations of Connecticut State Agencies ("R.C.S.A.") Section 16-50j-73, the Connecticut Siting Council has been notified of the changes and will review the Company's proposal. Please accept this letter and attachments as notification under Section 16-50j-73 of construction which constitutes an exempt modification pursuant to R.C.S.A. Section 16-50j-72(b)(2).

The accompanying letter fully describes Cingular's proposal. However, if you have any questions or require any further information on our plans or the Siting Council's procedures, please call me at (860) 301-6378 or Mr. Derek Phelps, Executive Director, Connecticut Siting Council at (860) 827-2935.

David S. Malko, P.E.

Consultant for New Cingular Wireless



Honorable Mark D. Boughton, Mayor City of Danbury 155 Deer Hill Avenue Danbury, CT 06810

Re: Notice of Exempt Modifications to Various Facilities in the Towns of Stratford, Stamford, Danbury and Bridgeport, Connecticut

Dear Mr. Boughton,

As part of its merger and integration efforts, New Cingular Wireless PCS, LLC ("Cingular" or "the Company") intends to modify instrumentation and/or antenna configurations at certain wireless telecommunications facilities. As required by the Regulations of Connecticut State Agencies ("R.C.S.A.") Section 16-50j-73, the Connecticut Siting Council has been notified of the changes and will review the Company's proposal. Please accept this letter and attachments as notification under Section 16-50j-73 of construction which constitutes an exempt modification pursuant to R.C.S.A. Section 16-50j-72(b)(2).

The accompanying letter fully describes Cingular's proposal. However, if you have any questions or require any further information on our plans or the Siting Council's procedures, please call me at (860) 301-6378 or Mr. Derek Phelps, Executive Director, Connecticut Siting Council at (860) 827-2935.

Sincerely,

David S. Malko, P.E.

Consultant for New Cingular Wireless



Honorable John Fabrizi, Mayor City of Bridgeport City Hall Annex 999 Broad Street Bridgeport, CT 06604

Re: Notice of Exempt Modifications to Various Facilities in the Towns of Stratford, Stamford, Danbury and Bridgeport, Connecticut

Dear Mr. Fabrizi,

As part of its merger and integration efforts, New Cingular Wireless PCS, LLC ("Cingular" or "the Company") intends to modify instrumentation and/or antenna configurations at certain wireless telecommunications facilities. As required by the Regulations of Connecticut State Agencies ("R.C.S.A.") Section 16-50j-73, the Connecticut Siting Council has been notified of the changes and will review the Company's proposal. Please accept this letter and attachments as notification under Section 16-50j-73 of construction which constitutes an exempt modification pursuant to R.C.S.A. Section 16-50j-72(b)(2).

The accompanying letter fully describes Cingular's proposal. However, if you have any questions or require any further information on our plans or the Siting Council's procedures, please call me at (860) 301-6378 or Mr. Derek Phelps, Executive Director, Connecticut Siting Council at (860) 827-2935.

David S. Malko, P.E.

Consultant for New Cingular Wireless



CONNECTICUT SITING COUNCIL

Ten Franklin Square, New Britain, CT 06051 Phone: (860) 827-2935 Fax: (860) 827-2950 E-Mail: siting.council@po.state.ct.us www.ct.gov/csc

December 5, 2005

The Honorable John Fabrizi Mayor City of Bridgeport City Hall 999 Broad Street Bridgeport, CT 06604

RE:

EM-CING-138-135-034-015-051130 - New Cingular Wireless PCS, LLC notice of intent to modify existing telecommunications facilities located at 623 Honey Spot Road, Stratford; 555 Main Street, Stamford; 39 West Street, Danbury; Moses Mountain, Danbury; and 430 John Street, Bridgeport, Connecticut.

Dear Mayor Fabrizi:

The Connecticut Siting Council (Council) received this request to modify an existing telecommunications facility, pursuant to Regulations of Connecticut State Agencies Section 16-50j-72.

The Council will consider this item at the next meeting scheduled for December 14, 2005 at 1.30 p.m. in Hearing Room One, Ten Franklin Square, New Britain, Connecticut.

If you have any questions or comments regarding this proposal, please call me or inform the council by December 12, 2005.

Thank you for your cooperation and consideration.

Very truly yours,

. - . . .

SPP/CKS

S. Derek Phelps Executive Director

SDP/ap

Enclosure: Notice of Intent

c: Melanie J. Howlett, Assistant City Attorney, City of Bridgeport





CONNECTICUT SITING COUNCIL

Ten Franklin Square, New Britain, CT 06051 Phone: (860) 827-2935 Fax: (860) 827-2950 E-Mail: siting.council@po.state.ct.us www.ct.gov/csc

December 5, 2005

The Honorable Mark D. Boughton Mayor City of Danbury City Hall 155 Deer Hill Avenue Danbury, CT 06810

RE:

EM-CING-138-135-034-015-051130 - New Cingular Wireless PCS, LLC notice of intent to modify existing telecommunications facilities located at 623 Honey Spot Road, Stratford; 555 Main Street, Stamford; 39 West Street, Danbury; Moses Mountain, Danbury; and 430 John Street, Bridgeport, Connecticut.

Dear Mayor Boughton:

The Connecticut Siting Council (Council) received this request to modify an existing telecommunications facility, pursuant to Regulations of Connecticut State Agencies Section 16-50j-72.

The Council will consider this item at the next meeting scheduled for December 14, 2005 at 1.30 p.m. in Hearing Room One, Ten Franklin Square, New Britain, Connecticut.

If you have any questions or comments regarding this proposal, please call me or inform the council by December 12, 2005.

Thank you for your cooperation and consideration.

Very truly yours,

SPPIRKE

S. Derek Phelps Executive Director

SDP/ap

Enclosure: Notice of Intent

c: Dennis Elpern, City Planner, City of Danbury





CONNECTICUT SITING COUNCIL

Ten Franklin Square, New Britain, CT 06051 Phone: (860) 827-2935 Fax: (860) 827-2950 E-Mail: siting.council@po.state.ct.us www.ct.gov/csc

December 5, 2005

The Honorable Dannel P. Malloy Mayor City of Stamford Stamford Government Center 888 Washington Boulevard P. O. Box 10152 Stamford, CT 06904-2152

RE: EM-CING-138-135-034-015-051130 - New Cingular Wireless PCS, LLC notice of intent to modify existing telecommunications facilities located at 623 Honey Spot Road, Stratford; 555 Main Street, Stamford; 39 West Street, Danbury; Moses Mountain, Danbury; and 430 John Street, Bridgeport, Connecticut.

Dear Mayor Malloy:

The Connecticut Siting Council (Council) received this request to modify an existing telecommunications facility, pursuant to Regulations of Connecticut State Agencies Section 16-50j-72.

The Council will consider this item at the next meeting scheduled for December 14, 2005 at 1.30 p.m. in Hearing Room One, Ten Franklin Square, New Britain, Connecticut.

If you have any questions or comments regarding this proposal, please call me or inform the council by December 12, 2005.

Thank you for your cooperation and consideration.

Very truly yours,

5 DP/RKE

S. Derek Phelps Executive Director

SDP/ap

Enclosure: Notice of Intent

c: Robert Stein, Planning and Zoning Director, City of Stamford





CONNECTICUT SITING COUNCIL

Ten Franklin Square, New Britain, CT 06051 Phone: (860) 827-2935 Fax: (860) 827-2950 E-Mail: siting.council@po.state.ct.us www.ct.gov/csc

December 5, 2005

The Honorable James R. Miron Town Manager Town of Stratford Town Hall, Room 101 2725 Main Street Stratford, CT 06497

RE: EM-CING-138-135-034-015-051130 - New Cingular Wireless PCS, LLC notice of intent to modify existing telecommunications facilities located at 623 Honey Spot Road, Stratford; 555 Main Street, Stamford; 39 West Street, Danbury; Moses Mountain, Danbury; and 430 John Street, Bridgeport, Connecticut.

Dear Mr. Miron:

The Connecticut Siting Council (Council) received this request to modify an existing telecommunications facility, pursuant to Regulations of Connecticut State Agencies Section 16-50j-72.

The Council will consider this item at the next meeting scheduled for December 14, 2005 at 1.30 p.m. in Hearing Room One, Ten Franklin Square, New Britain, Connecticut.

If you have any questions or comments regarding this proposal, please call me or inform the council by December 12, 2005.

Thank you for your cooperation and consideration.

Very truly yours,

5 DP/RKE

S. Derek Phelps Executive Director

SDP/ap

Enclosure: Notice of Intent

c: Gary Lorentson, Planning & Zoning Administrator, Town of Stratford





BANK OF AMERICA SALEM, NEW HAMPSHIRE

DIV. SITE AQUISITION INC 184 ROCKINGHAM ROAD SUITE LONDONDERRY, NH 03053	A-C	54-49-114	11/4/2005
PAY TO THE ORDER OFConnecticut Siting Council		\$ *	**500.00
Five Hundred and 00/100***************	************	***************	****** DOLLARS
Connecticut Siting Council Ten Franklin Square New Britain, CT 06051			
MEMO Cingular Filing Fee "" 0 0 3 5 1 4 11"	::011400495:: 00898	1 7744 11"	L NP
SAI COMMUNICATIONS DIV. SITE AQUISITION INC.			3514
Connecticut Siting Council	Cingular Filing Fee	11/4/2005	500.00
	REG	EIVED 3 0 2005	

Cheeks Received EM or TS

Date Filed: 1//30/05

Filing or Field Review (circle one)

Tower Owner	Street Address & Town	Requester Name(s)	Payee Name
BECKER UC	623 HONEYSPOT ED STRATFORD, CT	CINGULAR (NEW G'NGUL 40)	Sti
SBC CINGULAR	555 14AN ST		
	STAMFORD, G		

SBC (CHGULAR) 39 WEST ST.
DANBURY, CT

List DO# if applicable:___

List DO# if applicable:

MOSES MOUNTAIN

DANBURY CSC Filing Name: EM - CING - 138 - 135 - 034 - 015 - 051130

2CC CONSULTANTS

BRIDGERORT, CT

List DO# if applicable:

(i.e., EM-BAM-001-990911)

BRIDGERORT, CT

RCC CONSULTANTS

G:\Carriann\Forms\EMTSChkred.doc